

# 采用增强型航天塑料的 TL7700-SEP 耐辐射电源电压监控器

## 1 特性

- VID V62/19602
- 耐辐射
  - 单粒子锁定 (SEL) 在 125°C 下的抗扰度可达 43MeV-cm<sup>2</sup>/mg
  - 每个晶圆批次的 RLAT 总电离剂量 (TID) 高达 20krad(Si)
- 增强型航天塑料
  - 受控基线
  - 金线
  - NiPdAu 铅涂层
  - 一个组装和测试基地
  - 一个制造基地
  - 支持军用 (–55°C 至 125°C) 温度范围
  - 延长了产品生命周期
  - 延长了产品变更通知
  - 产品可追溯性
  - 采用增强型模塑化合物实现低释气
- 可通过两个外部电阻器来调节检测电压
- 1.0% 检测电压容差 (25°C)
- 可调节检测电压的迟滞
- 宽工作电源电压范围:  
1.8V 至 40V
- 低功耗:  
 $I_{CC} = 0.6\text{mA}$  (典型值),  $V_{CC} = 40\text{V}$

## 2 应用

- 支持近地球轨道空间 应用
- 适用于卫星的电源监控器
- 监控 DPS、MCU、FPGA 和 ASIC

## 3 说明

TL7700-SEP 是一款专为用作微型计算机和微处理器系统中的复位控制器而设计的双极集成电路。使用两个外部电阻器可将检测电压设置为大于 0.5V 的任何值。

电路功能非常稳定, 电源电压范围为 1.8V 至 40V。由于具有最小电源电流, 因此该产品可用于交流线路供电应用、便携式电池供电应用和汽车 应用。


TL7700-SEP 器件的设计工作温度范围是 –55°C 至 125°C。

器件信息<sup>(1)</sup>

器件型号	封装	封装尺寸 (标称值)
V62/19602	TSSOP (8)	3.00mm × 4.40mm

(1) 如需了解所有可用封装, 请参阅产品说明书末尾的可订购产品附录。

功能方框图



## 目录


<b>1</b>	<b>特性</b> .....	<b>1</b>	8.3	Feature Description .....	<b>11</b>
<b>2</b>	<b>应用</b> .....	<b>1</b>	8.4	Device Functional Modes .....	<b>12</b>
<b>3</b>	<b>说明</b> .....	<b>1</b>	<b>9</b>	<b>Application and Implementation</b> .....	<b>13</b>
<b>4</b>	<b>修订历史记录</b> .....	<b>2</b>	9.1	Application Information .....	<b>13</b>
<b>5</b>	<b>Pin Configuration and Functions</b> .....	<b>3</b>	9.2	Typical Application .....	<b>13</b>
<b>6</b>	<b>Specifications</b> .....	<b>4</b>	<b>10</b>	<b>Power Supply Recommendations</b> .....	<b>15</b>
6.1	Absolute Maximum Ratings .....	<b>4</b>	<b>11</b>	<b>Layout</b> .....	<b>15</b>
6.2	ESD Ratings .....	<b>4</b>	11.1	Layout Guidelines .....	<b>15</b>
6.3	Recommended Operating Conditions .....	<b>4</b>	11.2	Layout Example .....	<b>15</b>
6.4	Thermal Information .....	<b>4</b>	<b>12</b>	<b>器件和文档支持</b> .....	<b>16</b>
6.5	Electrical Characteristics .....	<b>5</b>	12.1	接收文档更新通知 .....	<b>16</b>
6.6	Switching Characteristics .....	<b>5</b>	12.2	社区资源 .....	<b>16</b>
6.7	Typical Characteristics .....	<b>6</b>	12.3	商标 .....	<b>16</b>
<b>7</b>	<b>Parameter Measurement Information</b> .....	<b>8</b>	12.4	静电放电警告 .....	<b>16</b>
<b>8</b>	<b>Detailed Description</b> .....	<b>10</b>	12.5	术语表 .....	<b>16</b>
8.1	Overview .....	<b>10</b>	<b>13</b>	<b>机械、封装和可订购信息</b> .....	<b>17</b>
8.2	Functional Block Diagram .....	<b>10</b>			

## 4 修订历史记录

注：之前版本的页码可能与当前版本有所不同。

日期	修订版本	说明
2019 年 3 月	*	初始发行版。

## 5 Pin Configuration and Functions



NC – No internal connection

### Pin Functions

PIN		I/O	DESCRIPTION
NAME	NO.		
CT	1	I/O	Timing capacitor connection. This terminal sets the RESET output pulse duration ( $t_{po}$ ). It is connected internally to a 15- $\mu$ A constant-current source. There is a limit on the switching speed of internal elements; even if CT is set to 0, response speeds remain at approximately 5 to 10 $\mu$ s. If CT is open, the device can be used as an adjustable-threshold noninverting comparator. If CT is low, the internal output-stage comparator is active, and the RESET output transistor is on. An external voltage must not be applied to this terminal due to the internal structure of the device. Therefore, drive the device using an open-collector transistor, FET, or 3-state buffer (in the low-level or high-impedance state).
GND	4	—	Ground Keep this terminal as low impedance as possible to reduce circuit noise.
NC	3, 6, 7	—	No internal connection
RESET	8	O	Reset output This terminal can be connected directly to a system that resets in the active-low state. A pullup resistor usually is required because the output is an npn open-collector transistor. An additional transistor should be connected when the active-high reset or higher output current is required.
SENSE	2	I	Voltage sense This terminal has a threshold level of 500 mV. The sense voltage and hysteresis can be set at the same time when the two voltage-dividing resistors are connected. The reference voltage is temperature compensated to inhibit temperature drift in the threshold voltage within the operating temperature range.
V <sub>CC</sub>	5	—	Power supply This terminal is used in an operating-voltage range of 1.8 V to 40 V.

## 6 Specifications

### 6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)<sup>(1)</sup>

	MIN	MAX	UNIT
V <sub>CC</sub> Supply voltage <sup>(2)</sup>		41	V
V <sub>s</sub> SENSE input voltage	−0.3	41	V
V <sub>OH</sub> Output voltage (off state)		41	V
I <sub>OL</sub> Output current (on state)		5	mA
T <sub>J</sub> Operating virtual-junction temperature		150	°C
T <sub>stg</sub> Storage temperature	−65	150	°C

- (1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- (2) All voltage values are with respect to the network ground terminal.

### 6.2 ESD Ratings

	VALUE	UNIT
V <sub>(ESD)</sub> Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001 <sup>(1)</sup>	500
	Charged-device model (CDM), per JEDEC specification JESD22-C101 <sup>(2)</sup>	1000

- (1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
- (2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

### 6.3 Recommended Operating Conditions

	MIN	MAX	UNIT
V <sub>CC</sub> Supply voltage	1.8	40	V
I <sub>OL</sub> Low-level output current		3	mA
T <sub>A</sub> Operating free-air temperature	−55	125	°C

### 6.4 Thermal Information

THERMAL METRIC <sup>(1)</sup>	TL7700-SEP	UNIT
	PW (TSSOP)	
	8 PINS	
R <sub>θJA</sub> Junction-to-ambient thermal resistance	172.9	°C/W
R <sub>θJC(top)</sub> Junction-to-case (top) thermal resistance	56.6	°C/W
R <sub>θJB</sub> Junction-to-board thermal resistance	101.2	°C/W
ψ <sub>JT</sub> Junction-to-top characterization parameter	5.2	°C/W
ψ <sub>JB</sub> Junction-to-board characterization parameter	99.6	°C/W

- (1) For more information about traditional and new thermal metrics, see the [Semiconductor and IC package thermal metrics](#) application report.

## 6.5 Electrical Characteristics

 $V_{CC} = 3\text{ V}$  (unless otherwise noted)

PARAMETER	TEST CONDITIONS	$T_A$	MIN	TYP	MAX	UNIT
$V_s$ SENSE input voltage		$-55^{\circ}\text{C}$ to $125^{\circ}\text{C}$	490		520	mV
$I_s$ SENSE input current	$V_s = 0.4\text{ V}$	$25^{\circ}\text{C}$	2	2.5	3	$\mu\text{A}$
		$-55^{\circ}\text{C}$ to $125^{\circ}\text{C}$	1.5		3.5	
$I_{CC}$ Supply current	$V_{CC} = 40\text{ V}$ , $V_s = 0.6\text{ V}$ , no load	$25^{\circ}\text{C}$		0.6	1	mA
$V_{OL}$ Low-level output voltage	$I_{OL} = 1.5\text{ mA}$	$25^{\circ}\text{C}$			0.4	V
	$I_{OL} = 3\text{ mA}$	$25^{\circ}\text{C}$			0.8	
$I_{OH}$ High-level output current	$V_{OH} = 40\text{ V}$ , $V_s = 0.6\text{ V}$	$-55^{\circ}\text{C}$ to $125^{\circ}\text{C}$			1	$\mu\text{A}$
$I_{CT}$ Timing-capacitor charge current	$V_s = 0.6\text{ V}$	$25^{\circ}\text{C}$	11	15	19	$\mu\text{A}$

## 6.6 Switching Characteristics

 $V_{CC} = 3\text{ V}$ ,  $T_A = 25^{\circ}\text{C}$  (unless otherwise noted)

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
$t_{pi}$ SENSE pulse duration	$C_T = 0.01\text{ }\mu\text{F}$ (see <a href="#">Figure 17</a> )	2			$\mu\text{s}$
$t_{po}$ Output pulse duration	$C_T = 0.01\text{ }\mu\text{F}$ (see <a href="#">Figure 17</a> )	0.5	1	1.5	ms
$t_r$ Output rise time	$C_T = 0.01\text{ }\mu\text{F}$ , $R_L = 2.2\text{ k}\Omega$ , $C_L = 100\text{ pF}$ (see <a href="#">Figure 17</a> )			15	$\mu\text{s}$
$t_f$ Output fall time	$C_T = 0.01\text{ }\mu\text{F}$ , $R_L = 2.2\text{ k}\Omega$ , $C_L = 100\text{ pF}$ (see <a href="#">Figure 17</a> )			0.5	$\mu\text{s}$
$t_{pd}$ Propagation delay time, SENSE to output	$C_T = 0.01\text{ }\mu\text{F}$ (see <a href="#">Figure 17</a> )			10	$\mu\text{s}$

## 6.7 Typical Characteristics

Data at high and low temperatures are applicable only within the recommended operating conditions.




Figure 1. Supply Current vs Supply Voltage




Figure 2. Timing Capacitor Charge Current vs Supply Voltage




Figure 3.  $V_{OL}$  vs  $I_{OL}$




Figure 4. Sense Input Voltage vs Temperature




Figure 5. Sense Input Current vs Sense Input Voltage




Figure 6. Output Pulse Duration vs Timing Capacitor

## Typical Characteristics (continued)

Data at high and low temperatures are applicable only within the recommended operating conditions.




Figure 7.  $V_{CC}$  vs Output Waveform 1 - See Figure 8




Figure 8.  $V_{CC}$  vs Output Test Circuit 1




Figure 9.  $V_{CC}$  vs Output Waveform 2 - See Figure 10




Figure 10.  $V_{CC}$  vs Output Test Circuit 2




Figure 11.  $V_{CC}$  vs Output Waveform 3 - See Figure 12






Figure 12.  $V_{CC}$  vs Output Test Circuit 3


## 7 Parameter Measurement Information



**Figure 13.  $V_{CC}$  vs  $I_{CC}$  Measurement Circuit**




**Figure 14.  $V_{CC}$  vs  $I_{CT}$  Measurement Circuit**




**Figure 15.  $I_{OL}$  vs  $V_{OL}$  Measurement Circuit**



## Parameter Measurement Information (continued)



**Figure 16.  $V_s$  and  $I_s$  Characteristics Measurement Circuit**



**Figure 17. Switching Characteristics Measurement Circuit**


## 8 Detailed Description

### 8.1 Overview

The TL7700-SEP is a bipolar integrated circuit designed for use as a reset controller in microcomputer and microprocessor systems. The SENSE voltage can be set to any value greater than 0.5 V using two external resistors. The hysteresis value of the sense voltage also can be set by the same resistors. The device includes a precision voltage reference, fast comparator, timing generator, and output driver, so it can generate a power-on reset signal in a digital system.

The TL7700-SEP has an internal 1.5-V temperature-compensated voltage reference from which all function blocks are supplied. Circuit function is very stable, with supply voltage in the 1.8-V to 40-V range. Minimum supply current allows use with ac line operation and portable battery operation.

### 8.2 Functional Block Diagram



Copyright © 2016, Texas Instruments Incorporated

 NOTE:  $I_{CT} = 15\text{ }\mu\text{A (Typ)}$ ,  $I_s = 2.5\text{ }\mu\text{A (Typ)}$

## 8.3 Feature Description

### 8.3.1 Sense-Voltage Setting

The SENSE terminal input voltage,  $V_s$ , of the TL7700-SEP typically is 500 mV. By using two external resistors, the circuit designer can obtain any sense voltage over 500 mV. In Figure 18, the sensing voltage,  $V_{s'}$ , is calculated as:

$$V_{s'} = V_s \times (R1 + R2) / R2$$

where

- $V_s = 490 \text{ mV to } 520 \text{ mV}$  over temperature range (1)




Figure 18. Setting the Sense Voltage


### 8.3.2 Sense-Voltage Hysteresis Setting

If the sense voltage ( $V_{s'}$ ) does not have hysteresis in it and the voltage on the sensing line contains ripples, the resetting of TL7700-SEP will be unstable. Hysteresis is added to the sense voltage to prevent such problems. As shown in Figure 19, the hysteresis ( $V_{hys}$ ) is added and the value is determined as:

$$V_{hys} = I_s \times R1$$

where

- $I_s = 1.5 \text{ } \mu\text{A to } 3.5 \text{ } \mu\text{A}$  over temperature range (2)



NOTE: The sense voltage,  $V_{s'}$ , is different from the SENSE terminal input voltage,  $V_s$ .  $V_s$  normally is 500 mV for triggering.

Figure 19.  $V_{CC}$ -RESET Timing Chart

## Feature Description (continued)

### 8.3.3 Output Pulse-Duration Setting

Constant-current charging starts on the timing capacitor when the sensing-line voltage reaches the TL7700-SEP sense voltage. When the capacitor voltage exceeds the threshold level of the output drive comparator,  $\overline{\text{RESET}}$  changes from a low to a high level. The output pulse duration is the time between the point when the SENSE-pin voltage exceeds the threshold level and the point when the  $\overline{\text{RESET}}$  output changes from a low level to a high level. When the TL7700-SEP is used for system power-on reset, the output pulse duration,  $t_{po}$ , must be set longer than the power rise time. The value of  $t_{po}$  is:

$$t_{po} = C_t \times 10^5 \text{ seconds}$$


where

- $C_t$  is the timing capacitor in farads (3)

There is a limit on the device response speed. Even if  $C_t = 0$ ,  $t_{po}$  is not 0, but approximately 5  $\mu\text{s}$  to 10  $\mu\text{s}$ . Therefore, when the TL7700-SEP is used as a comparator with hysteresis without connecting  $C_t$ , switching speeds ( $t_r/t_f$ ,  $t_{po}/t_{pd}$ , and so forth) must be considered.

## 8.4 Device Functional Modes

Figure 20 describes how the  $\overline{\text{RESET}}$  output pin responds to a change in the voltage at the SENSE pin. When the SENSE pin drops below 500 mV, the  $\overline{\text{RESET}}$  pin is pulled low.



NOTE: The sense voltage,  $V_{s'}$ , is different from the SENSE terminal input voltage,  $V_s$ .  $V_{s'}$  normally is 500 mV for triggering.

**Figure 20.  $V_{CC}$  RESET Response and Timing**

## 9 Application and Implementation

### NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

### 9.1 Application Information

The TL7700-SEP supply-voltage supervisor allows for any voltage greater than 500 mV to be monitored. This flexibility allows it to be used in many applications from FPGAs and microcontrollers to supply monitoring.

### 9.2 Typical Application

Figure 21 shows an application where the TL7700-SEP device is being used to sense the voltage supply for a microcontroller that is supplied with 5 V. If the sense voltage drops below 4.5 V, the RESET pin is pulled LOW, signaling the microcontroller to reset.




Figure 21. 5-V Supply Voltage Supervision

#### 9.2.1 Design Requirements

- When the TL7700-SEP is used for system power-on reset, the output pulse duration,  $t_{po}$ , must be set longer than the power rise time. The value of  $t_{po}$  is:  $t_{po} = C_t \times 10^5$  seconds.
- The RESET output is an open-collector output, so a pullup resistor is required.

#### 9.2.2 Detailed Design Procedure


The SENSE terminal input voltage,  $V_s$ , for TL7700-SEP is typically 500 mV. By using two external resistors, any sense voltage over 500 mV can be sensed.

Resistor R1 should be selected first to set the desired hysteresis. See the [Sense-Voltage Hysteresis Setting](#) section for detailed information on how to set the hysteresis.

Resistor R2 should then be selected based on the R1 value and the desired  $V_s$  voltage. In Figure 18, the sensing voltage,  $V_s$ , is calculated as:  $V_s = V_{cc} \times (R1 + R2) / R2$

## Typical Application (continued)

### 9.2.3 Application Curve



**Figure 22. SENSE Input Voltage vs Temperature**

## 10 Power Supply Recommendations


The TL7700-SEP device will operate within the supply range specified in [Recommended Operating Conditions](#). The device risks permanent damage over the voltage specified in [Absolute Maximum Ratings](#).

## 11 Layout

### 11.1 Layout Guidelines

As the  $\overline{\text{RESET}}$  pin is an open collector output, a pullup resistor is required to ensure the output is high when the output transistor is off. The SENSE resistors should be placed as close to the SENSE pin as possible to avoid introducing noise to the pin.

### 11.2 Layout Example



**Figure 23. TL7700-SEP Layout**

## 12 器件和文档支持

### 12.1 接收文档更新通知

要接收文档更新通知，请导航至 [TI.com.cn](http://TI.com.cn) 上的器件产品文件夹。单击右上角的 [通知我](#) 进行注册，即可每周接收产品信息更改摘要。有关更改的详细信息，请查看任何已修订文档中包含的修订历史记录。

### 12.2 社区资源

下列链接提供到 TI 社区资源的连接。链接的内容由各个分销商“按照原样”提供。这些内容并不构成 TI 技术规范，并且不一定反映 TI 的观点；请参阅 TI 的 [《使用条款》](#)。

**TI E2E™ Online Community** *TI's Engineer-to-Engineer (E2E) Community*. Created to foster collaboration among engineers. At [e2e.ti.com](http://e2e.ti.com), you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

**Design Support** *TI's Design Support* Quickly find helpful E2E forums along with design support tools and contact information for technical support.

### 12.3 商标

E2E is a trademark of Texas Instruments.  
All other trademarks are the property of their respective owners.

### 12.4 静电放电警告



ESD 可能会损坏该集成电路。德州仪器 (TI) 建议通过适当的预防措施处理所有集成电路。如果不遵守正确的处理措施和安装程序，可能会损坏集成电路。

ESD 的损坏小至导致微小的性能降级，大至整个器件故障。精密的集成电路可能更容易受到损坏，这是因为非常细微的参数更改都可能会导致器件与其发布的规格不相符。

### 12.5 术语表

**SLYZ022** — *TI 术语表*。

这份术语表列出并解释术语、缩写和定义。



## 13 机械、封装和可订购信息

以下页面包含机械、封装和可订购信息。这些信息是指定器件的最新可用数据。数据如有变更，恕不另行通知，且不会对此文档进行修订。如需获取此产品说明书的浏览器版本，请查阅左侧的导航栏。

## 重要声明和免责声明

TI 均以“原样”提供技术性 & 可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证其中不含任何瑕疵，且不做任何明示或暗示的担保，包括但不限于对适销性、适合某特定用途或不侵犯任何第三方知识产权的暗示担保。

所述资源可供专业开发人员应用 TI 产品进行设计使用。您将对以下行为独自承担全部责任：(1) 针对您的应用选择合适的 TI 产品；(2) 设计、验证并测试您的应用；(3) 确保您的应用满足相应标准以及任何其他安全、安保或其他要求。所述资源如有变更，恕不另行通知。TI 对您使用所述资源的授权仅限于开发资源所涉及 TI 产品的相关应用。除此之外不得复制或展示所述资源，也不提供其它 TI 或任何第三方的知识产权授权许可。如因使用所述资源而产生任何索赔、赔偿、成本、损失及债务等，TI 对此概不负责，并且您须赔偿由此对 TI 及其代表造成的损害。

TI 所提供产品均受 TI 的销售条款 (<http://www.ti.com.cn/zh-cn/legal/termsofsale.html>) 以及 [ti.com.cn](http://www.ti.com.cn) 上或随附 TI 产品提供的其他可适用条款的约束。TI 提供所述资源并不扩展或以其他方式更改 TI 针对 TI 产品所发布的可适用的担保范围或担保免责声明。

邮寄地址：上海市浦东新区世纪大道 1568 号中建大厦 32 楼，邮政编码：200122  
Copyright © 2019 德州仪器半导体技术（上海）有限公司

## PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
TL7700CMPWPSEP	ACTIVE	TSSOP	PW	8	150	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7700SP	<a href="#">Samples</a>
TL7700CMPWTPSEP	ACTIVE	TSSOP	PW	8	250	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7700SP	<a href="#">Samples</a>
V62/19602-01XE	ACTIVE	TSSOP	PW	8	250	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7700SP	<a href="#">Samples</a>
V62/19602-01XE-T	ACTIVE	TSSOP	PW	8	150	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7700SP	<a href="#">Samples</a>

(1) The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBSELETE:** TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".

**RoHS Exempt:** TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.

**Green:** TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and

continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.




In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



## PACKAGE OUTLINE

## TSSOP - 1.2 mm max height

## SMALL OUTLINE PACKAGE



4221848/A 02/2015


NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 mm per side.
4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
5. Reference JEDEC registration MO-153, variation AA.



**PW0008A**

## TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



LAND PATTERN EXAMPLE  
SCALE:10X



SOLDER MASK DETAILS  
NOT TO SCALE

4221848/A 02/2015

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.


7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.

## EXAMPLE STENCIL DESIGN

PW0008A

TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



SOLDER PASTE EXAMPLE  
BASED ON 0.125 mm THICK STENCIL  
SCALE:10X

4221848/A 02/2015

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

## 重要声明和免责声明

TI 均以“原样”提供技术性 & 可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证其中不含任何瑕疵，且不做任何明示或暗示的担保，包括但不限于对适销性、适合某特定用途或不侵犯任何第三方知识产权的暗示担保。

所述资源可供专业开发人员应用 TI 产品进行设计使用。您将对以下行为独自承担全部责任：(1) 针对您的应用选择合适的 TI 产品；(2) 设计、验证并测试您的应用；(3) 确保您的应用满足相应标准以及任何其他安全、安保或其他要求。所述资源如有变更，恕不另行通知。TI 对您使用所述资源的授权仅限于开发资源所涉及 TI 产品的相关应用。除此之外不得复制或展示所述资源，也不提供其它 TI 或任何第三方的知识产权授权许可。如因使用所述资源而产生任何索赔、赔偿、成本、损失及债务等，TI 对此概不负责，并且您须赔偿由此对 TI 及其代表造成的损害。

TI 所提供产品均受 TI 的销售条款 (<http://www.ti.com.cn/zh-cn/legal/termsofsale.html>) 以及 [ti.com.cn](http://www.ti.com.cn) 上或随附 TI 产品提供的其他可适用条款的约束。TI 提供所述资源并不扩展或以其他方式更改 TI 针对 TI 产品所发布的可适用的担保范围或担保免责声明。

邮寄地址：上海市浦东新区世纪大道 1568 号中建大厦 32 楼，邮政编码：200122  
Copyright © 2020 德州仪器半导体技术（上海）有限公司