

Sample &

🖥 Buy



TAS5614LA

ZHCS930A - MAY 2012 - REVISED MARCH 2015

TAS5614LA 150W 立体声/300W 单声道 PurePath™ HD 数字输入 D 类功率级

Technical

Documents

特性 1

- PurePath[™] HD 集成反馈提供:
 - 1W 功率/4Ω 负载条件下的总谐波失真 (THD) 为 0.03%
 - 电源抑制比 (PSRR) > 65dB (无输入信号)
 - (A 加权) 信噪比 (SNR) > 105dB
- 用于控制 G 类电源的预钳位输出
- 通过使用 60mΩ 输出金属氧化物半导体场效应晶体 管 (MOSFET) 减小了散热器体积,满输出功率时效 率 > 90%
- 总谐波失真+噪声 (THD+N) 为 10% 时的输出功率
 - 150W/4Ω,桥接负载 (BTL) 立体声配置
 - 300W/2Ω,并行桥接负载 (PBTL) 单声道配置
- THD+N 为 1% 时的输出功率
 - 125W/4Ω,桥接负载 (BTL) 立体声配置
 - 65W/8Ω,桥接负载 (BTL) 立体声配置
- 启动时无喀哒声和噼啪声
- 采用具有错误报告功能的自我保护设计,包含欠压 保护 (UVP)、过热保护和短路保护
- 采用推荐的系统设计时,符合电磁干扰 (EMI) 标准
- 采用 44 引脚散热薄型小外形尺寸 (HTSSOP) • (DDV) 封装,减小了电路板尺寸
- 2 应用
- 蓝光碟™ 和 DVD 接收器
- 高功率条形音响
- 有源超低音扬声器和有源扬声器
- 微型 Combo 系统 ٠

3 说明

Tools &

Software

TAS5614LA 器件是一款基于 TAS5614LA 的功能优化 D 类功率放大器。

Support &

Community

2.2

TAS5614LA 使用大型金属氧化物半导体场效应晶体管 (MOSFET) 提升功率效率,并采用新型栅极驱动方案 降低空闲状态下和输出信号较低时的损耗,从而减小散 热器尺寸。

该器件可使用独特的预钳位输出信号来控制 G 类电 源。 这一优势与 TAS5614LA 的低空闲损耗和高功率 效率相结合,可实现行业领先水平的效率,从而确保构 建超级"绿色"系统。

TAS5614LA 使用恒定电压增益。 内部匹配增益电阻器 确保了一个高电源抑制比, 使得输出电压只取决于音频 输入电压并避免了任何电源的人工缺陷。

TAS5614LA 的高集成度使得放大器易于使用: 另外, 使用 TI 的参考原理图和 PCB 布局缩短了设计时间。 TAS5614LA 采用节省空间的表面贴装 44 引脚 HTSSOP 封装。

器件信息(1)

器件型号	封装	封装尺寸 (标称值)
TAS5614LA	HTSSOP (44)	14.00mm x 6.10mm

(1) 要了解所有可用封装,请见数据表末尾的可订购产品附录。



TAS5614LA 典型应用框图



目录

1	特性	1
2	应用	. 1
3	说明	1
4	修订历史记录	2

Pin Configuration and Functions 3

Specifications...... 4

Absolute Maximum Ratings 4 ESD Ratings...... 4

Recommended Operating Conditions 5

Thermal Information 5

6.6 Audio Specification Stereo (BTL)...... 7

7	Deta	ailed Description 12
	6.9	Typical Characteristics
	6.8	Audio Specification Mono (PBTL)8
	6.7	Audio Specification 4 Channels (SE) 7

修订历史记录 4

5 6

6.1

6.2

6.3 6.4

6.5

Changes from Original (May 2012) to Revision A

已添加 引脚配置和功能部分, ESD 额定值表,特性描述部分,器件功能模式,应用和实施部分,电源相关建议部分, 布局部分,器件和文档支持部分以及机械、封装和可订购信息部分.....1

	74	Our and and	40
	7.1	Overview	
	7.2	Functional Block Diagrams	13
	7.3	Feature Description	15
	7.4	Device Functional Modes	19
8	Арр	lication and Implementation	21
	8.1	Application Information	21
	8.2	Typical Applications	21
9	Pow	ver Supply Recommendations	31
10	Lay	out	31
	10.1	Layout Guidelines	31
	10.2	Layout Example	33
11	器件	和文档支持	35
	11.1	商标	35
	11.2	静电放电警告	35
	11.3	术语表	35
12	机械	载、封装和可订购信息	35
12	机械	、封装和可订购信息	

EXAS **ISTRUMENTS**

www.ti.com.cn

Page



Γ

5 Pin Configuration and Functions



Pin Functions

PIN			DESCRIPTION	
NAME	NO.	1/0/F*/	DESCRIPTION	
AVDD	13	Р	Internal voltage regulator, analog section	
BST_A	44	Р	Bootstrap pin, A-side	
BST_B	43	Р	Bootstrap pin, B-side	
BST_C	24	Р	Bootstrap pin, C-side	
BST_D	23	Р	Bootstrap pin, D-side	
CLIP	18	0	Clipping warning, open drain, active low	
C_START	7	0	Start-up ramp	
DVDD	8	Р	Internal voltage regulator, digital section	
FAULT	16	0	Shutdown signal, open drain, active low	
GND	9, 10, 11, 12, 25, 26, 33, 34, 41, 42	Р	Ground	
GVDD_AB	1	Р	Gate-drive voltage supply, AB-side	
GVDD_CD	22	Р	Gate-drive voltage supply, CD-side	
INPUT_A	5	I	PWM input signal for half-bridge A	
INPUT_B	6	I	PWM input signal for half-bridge B	
INPUT_C	14	I	PWM input signal for half-bridge C	
INPUT_D	15	I	PWM input signal for half-bridge D	
M1	19	I	Mode selection 1 (LSB)	
M2	20	I	Mode selection 2	
M3	21	I	Mode selection 3 (MSB)	
OC_ADJ	3	0	Overcurrent threshold programming pin	

(1) I = Input, O = Output, P = Power

Copyright © 2012-2015, Texas Instruments Incorporated

STRUMENTS

XAS

Pin Functions (continued)

PIN			DESCRIPTION	
NAME	NO.	1/0/P*/	DESCRIPTION	
OTW	17	0	Overtemperature warning, open drain, active low	
OUT_A	39, 40	0	Output, half-bridge A	
OUT_B	35	0	Output, half-bridge B	
OUT_C	32	0	Output, half-bridge C	
OUT_D	27, 28	0	Output, half-bridge D	
PVDD_AB	36, 37, 38	Р	PVDD supply for half-bridge A and B	
PVDD_CD	29, 30, 31	Р	PVDD supply for half-bridge C and D	
RESET	4	I	Device reset input, active low	
VDD	2	Р	Input power supply	
PowerPAD™	_	Р	Ground, connect to grounded heat sink	

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range unless otherwise noted (1)

	MIN	MAX	UNIT
VDD to GND, GVDD_X ⁽²⁾ to GND	-0.3	13.2	V
PVDD_X ⁽²⁾ to GND ⁽³⁾ , OUT_X to GND ⁽³⁾ , BST_X to GVDD_X ⁽²⁾⁽³⁾	-0.3	50	V
BST_X to GND ⁽³⁾⁽⁴⁾	-0.3	62.5	V
DVDD to GND	-0.3	4.2	V
AVDD to GND	-0.3	8.5	V
OC_ADJ, M1, M2, M3, C_START, INPUT_X to GND	-0.3	4.2	V
RESET, FAULT, OTW, CLIP, to GND	-0.3	4.2	V
Maximum continuous sink current (FAULT, OTW, CLIP)		9	mA
Maximum operating junction temperature, T _J	0	150	°C
Lead temperature		260	°C
Storage temperature, T _{stg}	-40	150	°C

(1) Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

(2) GVDD_X and PVDD_X represents a full bridge gate drive or power supply. GVDD_X is GVDD_AB or GVDD_CD, PVDD_X is PVDD_AB or PVDD_CD

(3) These voltages represents the DC voltage + peak AC waveform measured at the pin of the device in all conditions.

(4) Maximum BST_X to GND voltage is the sum of maximum PVDD to GND and GVDD to GND voltages minus a diode drop.

6.2 ESD Ratings

			VALUE	UNIT
V _(ESD)	Electrostatic discharge Human body model (HBM), per ANSI/ESD pins ⁽¹⁾ Charged device model (CDM), per JEDEC C101, all pins ⁽²⁾	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001, all pins ⁽¹⁾	2000	V
		Charged device model (CDM), per JEDEC specification JESD22-C101, all pins $^{\left(2\right)}$	500	V

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.

(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

				MIN	NOM	MAX	UNIT
PVDD_X	Full-bridge supply		DC supply voltage	12	36	38	V
GVDD_X	Supply for logic regu gate-drive circuitry	lators and	DC supply voltage	10.8	12	13.2	V
VDD	Digital regulator supp	oly voltage	DC supply voltage	10.8	12	13.2	V
		BTL	Output filter: $L = 10 \mu H. 1 \mu F.$	3.0	4.0		
RL	Load impedance	SE	Output AD modulation,	1.5	3.0		Ω
		PBTL	switching frequency > 350 kHz.	1.5	2.0		
L _{OUTPUT}	Output filter inductance		Minimum inductance at overcurrent limit, including inductor tolerance, temperature and possible inductor saturation	5			μH
F _{PWM}	PWM frame rate		352	384	500	kHz	
C _{PVDD}	PVDD close decoupl	ing capacit	ors	0.44	1		μF
C START	Ctart up romp conce	itor	BTL and PBTL configuration		100		nF
C_START	Stan-up ramp capac	nor	SE and 1xBTL+2xSE configuration		1		μF
R _{OC}	Overcurrent program resistor	nming	Resistor tolerance = 5%	24		33	kΩ
R _{OC_LATCHED}	Overcurrent program resistor	iming	Resistor tolerance = 5%	47	62	68	kΩ
TJ	Junction temperature	9		0		125	°C

6.4 Thermal Information

		TAS5614LA		
	THERMAL METRIC ⁽¹⁾	DDV (HTSSOP)	UNIT	
		44 PINS		
$R_{ extsf{ heta}JH}$	Junction-to-heat sink thermal resistance	2.3		
R _{0JC(top)}	Junction-to-case (top) thermal resistance	0.8		
$R_{\theta JB}$	Junction-to-board thermal resistance	2.1	°C 1.1/	
Ψ_{JT}	Junction-to-top characterization parameter	0.8	°C/VV	
Ψ _{JB}	Junction-to-board characterization parameter	2.1		
R _{0JC(bot)}	Junction-to-case (bottom) thermal resistance	n/a		

(1) For more information about traditional and new thermal metrics, see the IC Package Thermal Metrics application report, SPRA953.

TAS5614LA

ZHCS930A-MAY 2012-REVISED MARCH 2015

NSTRUMENTS www.ti.com.cn

ÈXAS

6.5 Electrical Characteristics

 $\underline{PVDD}_X = 36 \text{ V}, \text{ } \text{GVDD}_X = 12 \text{ V}, \text{ } \text{VDD} = 12 \text{ V}, \text{ } \text{T}_{\text{C}} \text{ (Case temperature)} = 75^{\circ}\text{C}, \text{ } \text{f}_{\text{S}} = 384 \text{ kHz}, \text{ } \text{unless otherwise specified}.$

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
INTERNAL VOLTAGE RE	GULATOR AND CURRENT CONSUMP	TION				
DVDD	Voltage regulator, only used as a reference node	VDD = 12 V	3.0	3.3	3.6	V
AVDD	Voltage regulator, only used as a reference node	VDD = 12 V		7.8		V
1		Operating, 50% duty cycle		20		
IVDD	VDD supply current	Idle, reset mode		20		MA
1	Coto oupply ourront por full bridge	50% duty cycle		9		٣A
GVDD_X	Gate-supply current per full-bhage	Reset mode		2		IIIA
		50% duty cycle without load		23		
I _{PVDD_X}	Full-bridge idle current	RESET low		1.9		mA
		VDD and GVDD_X at 0V		0.35		
OUTPUT-STAGE MOSFE	Ts					
R _{DS(on), LS}	Drain-to-source resistance, low side (LS)	$T_J = 25^{\circ}C$, excludes metalization		60	100	mΩ
R _{DS(on), HS}	Drain-to-source resistance, high side (HS)	GVDD = 12 V		60	100	mΩ
I/O PROTECTION						
V _{uvp,GVDD}	Undervoltage protection limit,			8.5		V
V _{uvp,GVDD, hyst} ⁽¹⁾	GVDD_X			0.7		V
V _{uvp,VDD}	Lindervoltage protection limit V/DD			8.5		V
V _{uvp,VDD, hyst} ⁽¹⁾	Undervoltage protection limit, VDD			0.7		V
V _{uvp,PVDD}				8.5		V
V _{uvp,PVDD,hyst} ⁽¹⁾	Ondervoltage protection limit, PVDD_X			0.7		V
OTW ⁽¹⁾	Overtemperature warning		115	125	135	°C
OTW _{hyst} ⁽¹⁾	Temperature drop needed below OTW temperature for OTW to be inactive after OTW event.			25		°C
OTE ⁽¹⁾	Overtemperature error		145	155	165	°C
OTE-OTW _{differential} ⁽¹⁾	OTE-OTW differential			30		°C
OTE _{HYST} ⁽¹⁾	A device reset is needed to clear FAULT after an OTE event			25		°C
OLPC	Overload protection counter	f _{PWM} = 384 kHz		2.6		ms
loc	Overcurrent limit protection	Resistor – programmable, nominal peak current in 1- Ω load, ROC = 24 k Ω		15		А
	Overcurrent limit protection, latched	Resistor – programmable, nominal peak current in 1- Ω load, ROC = 62 k Ω		15		A
I _{OCT}	Overcurrent response time	Time from application of short condition to Hi-Z of affected half bridge		150		ns
I _{PD}	Internal pulldown resistor at output of each half bridge	Connected when RESET is active to provide bootstrap charge. Not used in SE mode.		3		mA
STATIC DIGITAL SPECIF	ICATIONS					
V _{IH}	High level input voltage		1.9			V
V _{IL}	Low level input voltage	INF 01_A, WIT, WZ, W3, KESET			0.8	V
LEAKAGE	Input leakage current				100	μA
OTW / SHUTDOWN (FAU	ILT)					
R _{INT_PU}	Internal pullup resistance, OTW, CLIP, I	FAULT to DVDD	20	26	33	kΩ
V _{OH}	High level output voltage	Internal pullup resistor	3	3.3	3.6	V
V _{OL}	Low level output voltage	I _O = 4 mA		200	500	mV
FANOUT	Device fanout OTW, FAULT, CLIP	No external pullup		30		devices

(1) Specified by design.



6.6 Audio Specification Stereo (BTL)

Audio performance is recorded as a chipset consisting of a PWM Processor (modulation index limited to 97.7%) and a TAS5614LA power stage with PCB and system configurations in accordance with recommended guidelines. Audio frequency = 1 kHz, PVDD_X = 36 V, GVDD_X = 12 V, R_L = 4 Ω , f_s = 384 kHz, R_{oc} = 24 k Ω , T_c = 75°C, Output Filter: L_{DEM} = 10 μ H, C_{DEM} = 1 μ F, unless otherwise noted.

PARAMETER		TEST CONDITIONS	MIN T	P MAX	UNIT
р	Power output per channel	$R_L = 4 \Omega$, 10% THD+N	1:	50	\A/
F0		$R_L = 4 \Omega$, 1% THD+N	1:	25	vv
THD+N	Total harmonic distortion + noise	1-W, 1-kHz signal	0.03	%	
V _n	Output integrated noise	A-weighted, AES17 measuring filter	1	30	μV
V _{OS}	Output offset voltage	No signal		10 20	mV
SNR	Signal-to-noise ratio ⁽¹⁾	A-weighted, AES17 measuring filter	1)5	dB
DNR	Dynamic range	A-weighted, –60 dBFS (rel 1% THD+N)	1	05	dB
P _{idle}	Power dissipation due to Idle losses (IPVDD_X)	$P_{O} = 0$, channels switching ⁽²⁾	1	.6	W

(1) SNR is calculated relative to 1% THD-N output level.

(2) Actual system idle losses also are affected by core losses of output inductors.

6.7 Audio Specification 4 Channels (SE)

Audio performance is recorded as a chipset consisting of a PWM Processor (modulation index limited to 97.7%) and a TAS5614LA power stage with PCB and system configurations in accordance with recommended guidelines. Audio frequency = 1 kHz, PVDD_X = 36 V, GVDD_X = 12 V, R_L = 4 Ω , f_s = 384 kHz, R_{OC} = 24 k Ω , T_c = 75°C, Output Filter: L_{DEM} = 10 μ H, C_{DEM} = 1 μ F, C_{DCB} = 470 μ F, unless otherwise noted.

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
р	Power output per channel	$R_L = 3 \Omega$, 10% THD+N		50		14/
F0	Power output per channel	$R_L = 3 \Omega$, 1% THD+N		42		vv
THD+N	Total harmonic distortion + noise	1-W, 1-kHz signal		0.025%		
V _n	Output integrated noise	A-weighted, AES17 measuring filter		180		μV
SNR	Signal-to-noise ratio ⁽¹⁾	A-weighted, AES17 measuring filter		102		dB
DNR	Dynamic range	A-weighted, –60 dBFS (rel 1% THD+N)		102		dB
P _{idle}	Power dissipation due to Idle losses (IPVDD_X)	$P_{O} = 0$, channel switching ⁽²⁾		1.6		W

(1) SNR is calculated relative to 1% THD-N output level.

(2) Actual system idle losses also are affected by core losses of output inductors.

TAS5614LA

ZHCS930A - MAY 2012 - REVISED MARCH 2015



www.ti.com.cn

6.8 Audio Specification Mono (PBTL)

Audio performance is recorded as a chipset consisting of a PWM Processor (modulation index limited to 97.7%) and a TAS5614LA power stage with PCB and system configurations in accordance with recommended guidelines. Audio frequency = 1 kHz, PVDD_X = 36 V, GVDD_X = 12 V, R_L = 4 Ω , f_S = 384 kHz, R_{OC} = 24 k Ω , T_C = 75°C, Output Filter: L_{DEM} = 10 μ H, C_{DEM} = 1 μ F, unless otherwise noted.

	PARAMETER	TEST CONDITIONS	MIN TYP	MAX	UNIT
		$R_L = 2 \Omega$, 10%, THD+N	300		
		$R_L = 3 \Omega$, 10% THD+N	200		
Po	Dower output nor chonnel	$R_L = 4 \Omega$, 10% THD+N	160		14/
	Power output per channel	$R_L = 2 \Omega$, 1% THD+N	250		VV
		$R_L = 3 \Omega$, 1% THD+N	160		
		$R_L = 4 \Omega$, 1% THD+N	130		
THD+N	Total harmonic distortion + noise	1-W, 1-kHz signal	0.025%		
V _n	Output integrated noise	A-weighted, AES17 measuring filter	180		μV
V _{OS}	Output offset voltage	No signal	10	20	mV
SNR	Signal to noise ratio ⁽¹⁾	A-weighted, AES17 measuring filter	105		dB
DNR	Dynamic range	A-weighted, -60 dBFS (rel 1% THD)	105		dB
P _{idle}	Power dissipation due to idle losses (IPVDD_X)	$P_{O} = 0$, All channels switching ⁽²⁾	1.6		W

(1) SNR is calculated relative to 1% THD-N output level.

(2) Actual system idle losses are affected by core losses of output inductors.



6.9 Typical Characteristics

6.9.1 BTL Configuration

Measurement conditions are: 1 kHz, PVDD_X = 36 V, GVDD_X = 12 V, $R_L = 4 \Omega$, $f_S = 384$ kHz, $R_{OC} = 24 k\Omega$, $T_C = 75^{\circ}C$, Output Filter: $L_{DEM} = 10 \mu$ H, $C_{DEM} = 1 \mu$ F, 20-Hz to 20-kHz BW (AES17 low-pass filter), unless otherwise noted.



BTL Configuration (接下页)

Measurement conditions are: 1 kHz, PVDD_X = 36 V, GVDD_X = 12 V, R_L = 4 Ω , f_S = 384 kHz, R_{OC} = 24 k Ω , T_C = 75°C, Output Filter: L_{DEM} = 10 μ H, C_{DEM} = 1 μ F, 20-Hz to 20-kHz BW (AES17 low-pass filter), unless otherwise noted.



6.9.2 SE Configuration





6.9.3 PBTL Configuration





7 Detailed Description

7.1 Overview

TAS5614LA is a PWM input, audio PWM (class-D) amplifier. The output of the TAS5614LA can be configured for single-ended, BTL (Bridge-Tied Load) or parallel BTL (PBTL) output. It requires two rails for power supply, PVDD and 12 V (GVDD and VDD).

Functional Block Diagrams shows typical connections for BTL outputs. Detailed schematic can be viewed in TAS5614LA EVM user's guide (SLAU375).



7.2 Functional Block Diagrams



(1) Logic AND is inside or outside the microprocessor.

图 13. Typical System Block Diagram

TEXAS INSTRUMENTS

www.ti.com.cn

Functional Block Diagrams (接下页)







7.3 Feature Description

7.3.1 Power Supplies

To facilitate system design, the TAS5614LA needs only a 12-V supply in addition to the (typical) 36-V powerstage supply. An internal voltage regulator provides suitable voltage levels for the digital and low-voltage analog circuitry. Additionally, all circuitry requiring a floating voltage supply, for example, the high-side gate drive, is accommodated by built-in bootstrap circuitry requiring only an external capacitor for each half-bridge.

To provide outstanding electrical and acoustical characteristics, the PWM signal path including gate drive and output stage is designed as identical, independent half-bridges. For this reason, each half-bridge has separate bootstrap pins (BST_X) and each full-bridge has separate power stage supply (PVDD_X) and gate supply (GVDD_X) pins. Furthermore, an additional pin (VDD) is provided as supply for all common circuits. Although supplied from the same 12-V source, it is highly recommended to separate GVDD_AB, GVDD_CD, and VDD on the printed-circuit board (PCB) by RC filters (see application diagram for details). These RC filters provide the recommended high-frequency isolation. Special attention should be paid to placing all decoupling capacitors as close to their associated pins as possible. In general, inductance between the power supply pins and decoupling capacitors must be avoided. (See reference board documentation for additional information.)

Special attention should be paid to the power-stage power supply; this includes component selection, PCB placement, and routing. As indicated, each full-bridge has independent power-stage supply pins (PVDD_X). For optimal electrical performance, EMI compliance, and system reliability, it is important that each PVDD_X connection is decoupled with minimum 2×220 -nF ceramic capacitors placed as close as possible to each supply pin. TI recommends following the PCB layout of the TAS5614LA reference design. For additional information on recommended power supply and required components, see the application diagrams in this data sheet.

The 12-V supply should be from a low-noise, low-output-impedance voltage regulator. Likewise, the 36-V powerstage supply is assumed to have low output impedance and low noise. The power-supply sequence is not critical as facilitated by the internal power-on-reset circuit. Moreover, the TAS5614LA is fully protected against erroneous power-stage turn on due to parasitic gate charging when power supplies are applied. Thus, voltagesupply ramp rates (dV/dt) are noncritical within the specified range (see *Recommended Operating Conditions*).

7.3.1.1 Boot Strap Supply

For a properly functioning bootstrap circuit, a small ceramic capacitor must be connected from each bootstrap pin (BST_X) to the power-stage output pin (OUT_X). When the power-stage output is low, the bootstrap capacitor is charged through an internal diode connected between the gate-drive power-supply pin (GVDD_X) and the bootstrap pin. When the power-stage output is high, the bootstrap capacitor potential is shifted above the output potential and thus provides a suitable voltage supply for the high-side gate driver. In an application with PWM switching frequencies in the range from 300 kHz to 400 kHz, TI recommends to use 33-nF ceramic capacitors, size 0603 or 0805, for the bootstrap supply. These 33-nF capacitors ensure sufficient energy storage, even during minimal PWM duty cycles, to keep the high-side power stage FET (LDMOS) fully turned on during the remaining part of the PWM cycle.

7.3.2 System Power-Up and Power-Down Sequence

7.3.2.1 Powering Up

The TAS5614LA does not require a power-up sequence. The outputs of the H-bridges remain in a highimpedance state until the gate-drive supply voltage (GVDD_X) and VDD voltage are above the undervoltage protection (UVP) voltage threshold (see *Electrical Characteristics*). Although not specifically required, TI recommends holding RESET in a low state while powering up the device. This allows an internal circuit to charge the external bootstrap capacitors by enabling a weak pulldown of the half-bridge output.

7.3.2.2 Powering Down

The TAS5614LA does not require a power-down sequence. The device remains fully operational as long as the gate-drive supply (GVDD_X) voltage and VDD voltage are above the undervoltage protection (UVP) voltage threshold (see *Electrical Characteristics*). Although not specifically required, it is a good practice to hold RESET low during power down, thus preventing audible artifacts including pops or clicks.



Feature Description (接下页)

7.3.3 Start-up and Shutdown Ramp Sequence

The integrated start-up and stop sequence ensures a click and pop free startup and shutdown sequence of the amplifier. The start-up sequence uses a voltage ramp with a duration set by the CSTART capacitor. The sequence uses the input PWM signals to generate output PWM signals, hence input idle PWM should be present during both startup and shut down ramping sequences.

VDD, GVDD_X, and PVDD_X power supplies must be turned on and with settled outputs before starting the start-up ramp by setting RESET high.

During start-up and shutdown ramp the input PWM signals should be in muted condition with the PWM processor noise shaper activity turned off (50% duty cycle).

The duration of the start-up and shutdown ramp is 100 ms + X ms, where X is the CSTART capacitor value in nF.

TI recommends using 100-nF CSTART in BTL and PBTL mode and 1 μ F in SE mode configuration. This results in ramp times of 200 ms and 1.1 s, respectively. The longer ramp time in SE configuration allows charge and discharge of the output ac coupling capacitor without audible artifacts.



图 15. Start-up/Shutdown Ramp

7.3.4 Unused Output Channels

If all available output channels are not used, TI recommends disabling switching of unused output nodes to reduce power consumption. Furthermore by disabling unused output channels the cost of unused output LC demodulation filters can be avoided.

Disabling a channel is done by leave the bootstrap capacitor (BST) unstuffed and connecting the respective input to GND. The unused output pin(s) can be left floating. Please note that the PVDD decoupling capacitors still need to be mounted.

OPERATING MODE	PWM INPUT	OUTPUT CONFIGURATION	UNUSED CHANNEL	INPUT_A	INPUT_B	INPUT_C	INPUT_D	UNSTUFFED COMPONENT
000	2N + 1							BST_A and BST_B
001	1N + 1	2 x BTL	AB		GND PW/Mb	PWMc	PWMd	capacitors
010	2N + 1		CD	i wivia	I WIND	OND	OND	capacitors

表 1. Unused Output Channels



Feature Description (接下页)

OPERATING MODE	PWM INPUT	OUTPUT CONFIGURATION	UNUSED CHANNEL	INPUT_A	INPUT_B	INPUT_C	INPUT_D	UNSTUFFED COMPONENT
	1N + 1	4 x SE	А	GND	PWMb	PWMc	PWMd	BST_A capacitor
101			В	PWMa	GND	PWMc	PWMd	BST_B capacitor
101			С	PWMa	PWMb	GND	PWMd	BST_C capacitor
			D	PWMa	PWMb	PWMc	GND	BST_D capacitor

表 1. Unused Output Channels (接下页)

7.3.5 Device Protection System

The TAS5614LA contains advanced protection circuitry carefully designed to facilitate system integration and ease of use, as well as to safeguard the device from permanent failure due to a wide range of fault conditions such as short circuits, overload, overtemperature, and undervoltage. The TAS5614LA responds to a fault by immediately setting the power stage in a high-impedance (Hi-Z) state and asserting the FAULT pin low. In situations other than overload and overtemperature error (OTE), the device automatically recovers when the fault condition has been removed, that is, the supply voltage has increased.

The device will function on errors, as shown in the following table.

BTL MODE		PBTL MODE		SE MODE			
CHANNEL FAULT	TURNS OFF	CHANNEL FAULT	TURNS OFF	CHANNEL FAULT	TURNS OFF		
А	A+B	А	A+B+C+D	А	A+B		
В		В		В			
С	C+D	С		С	C+D		
D		D		D			

表 2. Device Protection

Bootstrap UVP does not shutdown according to the table, it shuts down the respective high-side FET.

7.3.6 Pin-to-Pin Short-Circuit Protection (PPSC)

The PPSC detection system protects the device from permanent damage if a power output pin (OUT_X) is shorted to GND or PVDD_X. For comparison, the OC protection system detects an overcurrent after the demodulation filter where PPSC detects shorts directly at the pin before the filter. PPSC detection is performed at start-up that is, when VDD is supplied, consequently a short to either GND or PVDD_X after system start-up will not activate the PPSC detection system. When PPSC detection is activated by a short on the output, all half-bridges are kept in a Hi-Z state until the short is removed, the device then continues the start-up sequence and starts switching. The detection is controlled globally by a two step sequence. The first step ensures that there are no shorts from OUT_X to GND, the second step tests that there are no shorts from OUT_X to PVDD_X. The total duration of this process is roughly proportional to the capacitance of the output LC filter. The typical duration is <15 ms/µF. While the <u>PPSC</u> detection is in progress, FAULT is kept low, and the device will not react to changes applied to the RESET pins. If no shorts are present the PPSC detection passes, and FAULT is released. A device reset will not start a new PPSC detection. PPSC detection is enabled in BTL and PBTL output configurations, the detection is not performed in SE mode. To prevent to tripping the PPSC detection system TI recommends not inserting resistive load to GND or PVDD_X.

7.3.7 Overtemperature Protection

The TAS5614LA has a two-level temperature-protection system that asserts an active-low warning signal (OTW) when the device junction temperature exceeds 125°C (typical). If the device junction temperature exceeds 155°C (typical), the device is put into thermal shutdown, resulting in all half-bridge outputs being set in the high-impedance (Hi-Z) state and FAULT being asserted low. OTE is latched in this case. To clear the OTE latch, RESET must be asserted. Thereafter, the device resumes normal operation.

TAS5614LA ZHCS930A – MAY 2012 – REVISED MARCH 2015

TEXAS INSTRUMENTS

www.ti.com.cn

7.3.8 Overtemperature Warning, OTW

The overtemperature warning OTW asserts when the junction temperature has exceeded recommended operating temperature. Operation at junction temperatures above OTW threshold is exceeding recommended operation conditions and is strongly advised to avoid.

If OTW asserts, action should be taken to reduce power dissipation to allow junction temperature to decrease until it gets below the OTW hysteresis threshold. This action can be decreasing audio volume or turning on a system cooling fan.

7.3.9 Undervoltage Protection (UVP) and Power-On Reset (POR)

The UVP and POR circuits of the TAS5614LA fully protect the device in any power-up/down and brownout situation. While powering up, the POR circuit resets the overload circuit (OLP) and ensures that all circuits are fully operational when the GVDD_X and VDD supply voltages reach stated in *Electrical Characteristics*. Although GVDD_X and VDD are independently monitored, a supply voltage drop below the UVP threshold on any VDD or <u>GVDD_X</u> pin results in all half-bridge outputs immediately being set in the high-impedance (Hi-Z) state and FAULT being asserted low. The device automatically resumes operation when all supply voltages have increased above the UVP threshold.

7.3.10 Error Reporting

Note that asserting RESET low forces the FAULT signal high, independent of faults being present. TI recommends monitoring the OTW signal using the system micro controller and responding to an overtemperature warning signal by, for example, turning down the volume to prevent further heating of the device resulting in device shutdown (OTE).

To reduce external component count, an internal pullup resistor to 3.3 V is provided on both FAULT and OTW outputs.

The FAULT, OTW, pins are active-low, open-drain outputs. Their function is for protection-mode signaling to a PWM controller or other system-control device.

Any fault resulting in device shutdown is signaled by the FAULT pin going low. Likewise, OTW goes low when the device junction temperature exceeds 125°C (see the following table).

FAULT	ΟΤΨ	DESCRIPTION
0	0	Overtemperature (OTE) or overload (OLP) or undervoltage (UVP)
0	1	Overload (OLP) or undervoltage (UVP)
1	0	Junction temperature higher than 125°C (overtemperature warning)
1	1	Junction temperature lower than 125°C and no OLP or UVP faults (normal operation)

表 3. Error Reporting

7.3.11 Fault Handling

If a fault situation occurs while in operation, the device will act accordingly to the fault being a global or a channel fault. A global fault is a chip-wide fault situation and will cause all PWM activity of the device to be shut down, and will assert FAULT low. A global fault is a latching fault and clearing FAULT and restart operation requires resetting the device by toggling RESET. Toggling RESET should never be allowed with excessive system temperature, so it is advised to monitor RESET by a system microcontroller and only allow releasing RESET (RESET high) if the OTW signal is cleared (high). A channel fault will result in shutdown of the PWM activity of the affected channel(s). Note that asserting RESET low forces the FAULT signal high, independent of faults being present. TI recommends monitoring the OTW signal using the system micro controller and responding to an over temperature warning signal by, for example, turning down the volume to prevent further heating of the device resulting in device shutdown (OTE).

FAULT or EVENT	FAULT or EVENT DESCRIPTION	GLOBAL or CHANNEL	REPORTING METHOD	LATCHED or SELF CLEARING	ACTION NEEDED TO CLEAR	OUTPUT FETs
PVDD_X UVP						
VDD UVP		Olahal			Increase affected supply	11: 7
GVDD_X UVP	vollage Fault	Giobai	TAOLT FIIT Sell Cleaning	voltage	ni-2	
AVDD UVP						
POR (DVDD UVP)	Power On Reset	Global	FAULT Pin	JLT Pin Self Clearing Allow DVDD to rise		H-Z
BST UVP	Voltage Fault	Channel (half bridge)	None	Self Clearing	Allow BST cap to recharge (low side on, VDD 12 V)	High Side Off
OTW	Thermal Warning	Global	OTW Pin	Self Clearing	Cool below lower OTW threshold	Normal operation
OTE (OTSD)	Thermal Shutdown	Global	FAULT Pin	Latched	Toggle RESET	Hi-Z
OLP (CBC >2.6 ms)	OC shutdown	Channel	FAULT Pin	Latched	Toggle RESET	Hi-Z
Latched OC (ROC > 47k)	OC shutdown	Channel	FAULT Pin	Latched	Toggle RESET	Hi-Z
CBC (24k < ROC < 33k)	OC Limiting	Channel	None	Self Clearing	reduce signal level or remove short	Flip state, cycle by cycle at fs/2
Stuck at Fault ⁽¹⁾ (1 to 3 channels)	No PWM	Channel	None	Self Clearing	resume PWM	Hi-Z
Stuck at Fault ⁽¹⁾ (All channels)	No PWM	Global	None	Self Clearing	resume PWM	Hi-Z
1) Stuck at Fault or	cure when input PW	M dropp bolow		M frama rata giyan in	Pasammandad Oparating (Conditions

表 4. Fault Handling

(1) Stuck at Fault occurs when input PWM drops below minimum PWM frame rate given in *Recommended Operating Conditions*.

7.3.12 Device Reset

When RESET is asserted low, all power-stage FETs in the four half-bridges are forced into a high-impedance (Hi-Z) state.

In BTL modes, to accommodate bootstrap charging prior to switching start, asserting the reset input low enables weak pulldown of the half-bridge outputs. In the SE mode, the output is forced into a high impedance state when <u>asserting</u> the reset input low. Asserting reset input low removes any fault information to be signaled on the FAULT output, that is, FAULT is forced high. A rising-edge transition on reset input allows the device to resume operation after an overload fault. To ensure thermal reliability, the rising edge of RESET must occur no sooner than 4 ms after the falling edge of FAULT.

7.4 Device Functional Modes

There are three main output modes that the user can configure the device as per application requirement. In addition there are two PWM modulation modes, AD and BD.

AD modulation can have single-ended (SE) or differential analog inputs. AD modulation can also be configured to have SE, BTL, BTL+SE, or PBTL outputs. BD modulation requires differential analog inputs.

BD modulation can only be configured in BTL or PTBL mode.

Device Functional Modes (接下页)

7.4.1 Mode Selection Pins

	MODE PINS	i	PWM	OUTPUT					MODE
M3	M2	M1	INPUT ⁽¹⁾	CONFIGURATION	INPUT A	INPUT B	INPUTC	INPUTD	MODE
0	0	0	2N + 1	2 x BTL	PWMa	PWMb	PWMc	PWMd	AD mode
0	0	1	1N + 1 ⁽²⁾	2 x BTL	PWMa	Unused	PWMc	Unused	AD mode
0	1	0	2N + 1	2 x BTL	PWMa	PWMb	PWMc	PWMd	BD mode
0	1	1	1N + 1 ⁽²⁾	1 x BTL + 2 x SE	PWMa	Unused	PWMc	PWMd	AD mode
1	0	0	2N + 1	1 x PBTL	PWMa	PWMb	0	0	AD mode
1	0	0	1N + 1 ⁽²⁾	1 x PBTL	PWMa	Unused	0	1	AD mode
1	0	0	2N + 1	1 x PBTL	PWMa	PWMb	1	0	BD mode
1	0	1	1N + 1	4 x SE ⁽³⁾	PWMa	PWMb	PWMc	PWMd	AD mode

 The 1N and 2N naming convention is used to indicate the number of PWM lines to the power stage per channel in a specific mode.
 Using 1N interface in BTL and PBTL mode results in increased DC offset on the output terminals.
 The 4xSE mode can be used as 1xBTL + 2xSE configuration by feeding a 2N PWM signal to either INPUT_AB or INPUT_CD for improved dc offset accuracy



8 Application and Implementation

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

8.1.1 System Design Consideration

A rising-edge transition on reset input allows the device to execute the startup sequence and starts switching.

Apply audio only according to the timing information for startup and shutdown sequence. That will start and stop the amplifier without audible artifacts in the output transducers.

The CLIP signal indicates that the output is approaching clipping (when output PWM starts skipping pulses due to loop filter saturation). The signal can be used to initiate an audio volume decrease or to adjust the power supply rail.

The device inverts the audio signal from input to output.

The DVDD and AVDD pins are not recommended to be used as a voltage source for external circuitry.

8.2 Typical Applications

The following sections discuss in detail three typical audio PWM (class-D) configurations:

- Differential input, stereo BTL outputs
- Differential input, mono PBTL output
- Single-ended inputs, quad single-ended outputs.



8.2.1 Typical BTL Application



图 16. Typical Differential (2N) BTL Application With AD Modulation Filters



PWM(-).

8.2.1.1 Design Requirements

See 8 16 for application schematic. In this application, differential PWM inputs are used with AD modulation from the PWM modulator (TAS5558). AD modulation scheme is defined as PWM(+) is opposite polarity from

8.2.1.2 Detailed Design Procedure

- Pin 1 GVDD_AB is the gate drive voltage for half-bridges A and B. This pin needs a 3.3-Ω isolation resistor and a 0.1-uF decoupling capacitor.
- Pin 2 VDD is the supply for internal voltage regulators AVDD and DVDD. This pin needs a 10-uF bulk capacitor and a 0.1-uF decoupling capacitor.
- Pin 3 Roc adjust is the overcurrent programming resistor. Depending on the application, this resistor can be between 24 k Ω to 68 k Ω .
- Pin 4 RESET pin when asserted, it keeps outputs Hi-Z and no PWM switching. This pin can be controlled by a microprocessor.
- Pins 5 and 6 These are PWM (+) and PWM (-) pins with signals provided by a PWM modulator such as TAS5558. These are PWM differential pair.
- Pin 7 Start-up ramp capacitor should be 0.1 uF for BTL configuration.
- Pin 8 Digital output supply pin is connected to 1-uF decoupling capacitor.
- Pins 9-12 Ground pins are connected to board ground.
- Pin 13 Analog output supply pin is connected to 1-uF decoupling capacitor.
- Pins 14 and 15 These are PWM (+) and PWM (–) pins with signals provided by a PWM modulator such as TAS5558. These are PWM differential pair.
- Pin 16 Fault pin can be monitored by a micro-controller via GPIO pin. System can decide to assert reset or shutdown.
- Pin 17 Overtemperature warning pin can be monitored by a microcontroller through a GPIO pin. System can decide to turn on fan or lower output power.
- Pin 18 Output clip indicator can be monitored by a microcontroller via a GPIO pin. System can decide to lower the volume.
- Pins 19-21 Mode pins set the input and output configurations. For this configuration M1-M3 are grounded. These mode pins must be hardware configured, such as, not through GPIO pins from a micro-controller.
- Pin 22 GVDD_CD is the gate drive voltage for half-bridges C and D. This pin needs a 3.3-Ω isolation resistor and a 0.1-uF decoupling capacitor.
- Pins 23, 24, 43, 44 Bootstrap pins for half-bridges A, B, C, and D. Connect 33 nF from this pin to corresponding output pins.
- Pins 25, 26, 33, 34, 41, 42 These ground pins should be used to ground decoupling capacitors from PVDD_X.

TAS5614LA

ZHCS930A - MAY 2012 - REVISED MARCH 2015

TAS5614LA

ZHCS930A-MAY 2012-REVISED MARCH 2015



www.ti.com.cn

8.2.1.3 Application Curves



8.2.2 Typical SE Configuration



图 19. Typical (1N) SE Application

TAS5614LA

ZHCS930A - MAY 2012 - REVISED MARCH 2015



8.2.2.1 Design Requirements

See 19 for application schematic. In this application, four single-ended PWM inputs are used with AD modulation from the PWM modulator such as the TAS5558. AD modulation scheme is defined as PWM(+) is opposite polarity from PWM(-). The single-ended (SE) output configuration is often used to drive 4 independent channels in one TAS5614LA device.

8.2.2.2 Detailed Design Procedure

- Pin 1 GVDD_AB is the gate drive voltage for half-bridges A and B. It needs a 3.3-Ω isolation resistor and a 0.1-uF decoupling capacitor.
- Pin 2 VDD is the supply for internal voltage regulators AVDD and DVDD. It needs a 10-uF bulk cap and a 0.1-uF decoupling capacitor.
- Pin 3 Roc adjust is the overcurrent programming resistor. Depending on the application, this resistor can be between 24 k Ω to 68 k Ω .
- Pin 4 RESET pin when asserted, it keeps outputs Hi-Z and no PWM switching. This pin can be controlled by a microprocessor.
- Pins 5 and 6 These are PWM (+) and PWM (-) pins with signals provided by a PWM modulator such as TAS5558. These are PWM differential pair.
- Pin 7 Start up ramp capacitor should be 1 uF for SE configuration.
- Pin 8 Digital output supply pin is connected to 1-uF decoupling cap.
- Pins 9-12 Ground pins are connected to board ground.
- Pin 13 Analog output supply pin is connected to 1-uF decoupling cap.
- Pins 14 and 15 These are PWM (+) and PWM (-) pins with signals provided by a PWM modulator such as TAS5558. These are PWM differential pair.
- Pin 16 Fault pin can be monitored by a microcontroller through GPIO pin. System can decide to assert reset or shutdown.
- Pin 17 Overtemperature warning pin can be monitored by a microcontroller through a GPIO pin. System can decide to turn on fan or lower output power.
- Pin 18 Output clip indicator can be monitored by a microcontroller through a GPIO pin. System can decide to lower the volume.
- Pins 19-21 Mode pins set the input and output configurations. For this configuration M1-M3 are grounded. These mode pins must be hardware configured, such as, not through GPIO pins from a microcontroller.
- Pin 22 GVDD_CD is the gate drive voltage for half-bridges C and D. This pin needs a 3.3-Ω isolation resistor and a 0.1-uF decoupling capacitor.
- Pins 23, 24, 43, 44 Bootstrap pins for half-bridges A, B, C, and D. Connect 33 nF from this pin to corresponding output pins.
- Pins 25, 26, 33, 34, 41, 42 These ground pins should be used to ground decoupling capacitors from PVDD_X.



8.2.2.3 Application Curves





8.2.3 Typical PBTL Configuration



图 22. Typical Differential (2N) PBTL Application With AD Modulation Filter



8.2.3.1 Design Requirements

See 22 for application schematic. In this application, one differential PWM input is used with AD modulation from the PWM modulator such as the TAS5558. AD modulation scheme is defined as PWM(+) is opposite polarity from PWM(-). The output PBTL configuration is often used to drive lower impedance load such as a subwoofer.

8.2.3.2 Detailed Design Procedure

- Pin 1 GVDD_AB is the gate drive voltage for half-bridges A and B. This pin needs a 3.3-Ω isolation resistor and a 0.1-uF decoupling capacitor.
- Pin 2 VDD is the supply for internal voltage regulators AVDD and DVDD. This pin needs a 10-uF bulk cap and a 0.1-uF decoupling capacitor.
- Pin 3 Roc adjust is the over-current programming resistor. Depending on the application, this resistor can be between 24 k Ω to 68 k Ω .
- Pin 4 RESET pin when asserted, it keeps outputs Hi-Z and no PWM switching. This pin can be controlled by a microprocessor.
- Pins 5 and 6 These are PWM (+) and PWM (-) pins with signals provided by a PWM modulator such as TAS5558. These are PWM differential pair.
- Pin 7 Start up ramp capacitor should be 0.1 uF for PBTL configuration.
- Pin 8 Digital output supply pin is connected to 1-uF decoupling capacitor.
- Pins 9-12 Ground pins are connected to board ground.
- Pin 13 Analog output supply pin is connected to 1-uF decoupling cap.
- Pins 14 and 15 These are PWM (+) and PWM (-) pins with signals provided by a PWM modulator such as TAS5558. These are PWM differential pair.
- Pin 16 Fault pin can be monitored by a microcontroller through GPIO pin. System can decide to assert reset or shutdown.
- Pin 17 Overtemperature warning pin can be monitored by a microcontroller through a GPIO pin. System can decide to turn on fan or lower output power.
- Pin 18 Output clip indicator can be monitored by a microcontroller through a GPIO pin. System can decide to lower the volume.
- Pins 19-21 Mode pins set the input and output configurations. For this configuration M1-M3 are grounded. These mode pins must be hardware configured, such as, not through GPIO pins from a microcontroller.
- Pin 22 GVDD_CD is the gate drive voltage for half-bridges C and D. It needs a 3.3-Ω isolation resistor and a 0.1-uF decoupling capacitor.
- Pins 23, 24, 43, 44 Bootstrap pins for half-bridges A, B, C, and D. Connect 33 nF from this pin to corresponding output pins.
- Pins 25, 26, 33, 34, 41, 42 These ground pins should be used to ground decoupling capacitors from PVDD_X.
- Pins 27, 28, 32, 35, 39, 40 Output pins from half-bridges A, B, C, and D. Connect appropriate bootstrap capacitors and differential LC filter as shown in 图 22.

TAS5614LA

ZHCS930A-MAY 2012-REVISED MARCH 2015



www.ti.com.cn

8.2.3.3 Application Curves





9 Power Supply Recommendations

The most important parameters are the absolute maximum rating on PVDD pins, bootstrap pins, and output pins. Over stress the device with higher that maximum voltage rating may shorten device lifetime operation and even cause device damage. Be sure that the specifications in *Specifications* are observed. For best audio performance, low ESR bulk caps are recommended. Depending on the application 470-µF capacitor or higher should be used. As always, decoupling capacitors must be placed no more than 1 mm from the power supply pins. If PCB space is not allowed for close placement of the decoupling capacitor, the decoupling capacitors can be placed on the back side of the device with vias. However, it still needs to be right below the pins.

10 Layout

10.1 Layout Guidelines

10.1.1 PCB Material Recommendation

FR-4 Glass Epoxy material with 1 oz. (35 µm) is recommended for use with the TAS5614LA. The use of this material can provide for higher power output, improved thermal performance, and better EMI margin (due to lower PCB trace inductance.

10.1.2 PVDD Capacitor Recommendation

The large capacitors used in conjunction with each full-bridge, are referred to as the PVDD Capacitors. These capacitors should be selected for proper voltage margin and adequate capacitance to support the power requirements. In practice, with a well designed system power supply, 1000 μ F, 50 V should support most applications. The PVDD capacitors should be low ESR type because they are used in a circuit associated with high-speed switching.

10.1.3 Decoupling Capacitor Recommendation

To design an amplifier that has robust performance, passes regulatory requirements, and exhibits good audio performance, good quality decoupling capacitors should be used. In practice, X5R or better should be used in this application.

The voltage of the decoupling capacitors should be selected in accordance with good design practices. Temperature, ripple current, and voltage overshoot must be considered. This fact is particularly true in the selection of the close decoupling capacitor that is placed on the power supply to each half-bridge. It must withstand the voltage overshoot of the PWM switching, the heat generated by the amplifier during high power output, and the ripple current created by high power output. A minimum voltage rating of 50V is required for use with a 36-V power supply.

See the TAS5614LADDVEVM user's guide, SLAU375, for more details including layout and bill of materials.

10.1.4 Circuit Component and Printed Circuit Board Recommendation

These requirements must be followed to achieve best performance and reliability and minimum ground bounce at rated output power of TAS5614LA.

10.1.4.1 Circuit Component Requirements

A number of circuit components are critical to performance and reliability. They include LC filter inductors and capacitors, decoupling capacitors and the heatsink. The best detailed reference for these is the TAS5614LA EVM BOM in the user's guide, which includes components that meet all the following requirements.

- High frequency decoupling capacitors: small high frequency decoupling capacitors are placed next to the IC to control switching spikes and keep high frequency currents in a tight loop to achieve best performance and reliability and EMC. They must be high quality ceramic parts with material like X7R or X5R and voltage ratings at least 30% greater than PVDD, to minimize loss of capacitance caused by applied dc voltage. (Capacitors made of materials like Y5V or Z5U should never be used in decoupling circuits or audio circuits because their capacitance falls dramatically with applied dc and ac voltage, often to 20% of rated value or less.)
- Bulk decoupling capacitors: large bulk decoupling capacitors are placed as close as possible to the IC to



Layout Guidelines (接下页)

stabilize the power supply at lower frequencies. They must be high quality aluminum parts with low ESR and ESL and voltage ratings at least 25% more than PVDD to handle power supply ripple currents and voltages

- LC filter inductors: to maintain high efficiency, short circuit protection and low distortion, LC filter inductors must be linear to at least the OCP limit and must have low DC resistance and core losses. For SCP, minimum working inductance, including all variations of tolerance, temperature and current level, must be 5 µH. Inductance variation of more than 1% over the output current range can cause increased distortion.
- LC filter capacitors: to maintain low distortion and reliable operation, LC filter capacitors must be linear to twice the peak output voltage. For reliability, capacitors must be rated to handle the audio current generated in them by the maximum expected audio output voltage at the highest audio frequency.
- Heatsink: The heatsink must be fabricated with the PowerPAD contact area spaced 1.0 mm ±0.01 mm above mounting areas that contact the PCB surface. It must be supported mechanically at each end of the IC. This mounting ensures the correct pressure to provide good mechanical, thermal and electrical contact with TAS5614LA PowerPAD. The PowerPAD contact area must be bare and must be interfaced to the PowerPAD with a thin layer (about 1 mil) of a thermal compound with high thermal conductivity.

10.1.4.2 Printed Circuit Board Requirements

PCB layout, audio performance, EMC and reliability are linked closely together, and solid grounding improves results in all these areas. The circuit produces high, fast-switching currents, and care must be taken to control current flow and minimize voltage spikes and ground bounce at IC ground pins. Critical components must be placed for best performance and PCB traces must be sized for the high audio currents that the IC circuit produces.

Grounding: ground planes must be used to provide the lowest impedance and inductance for power and audio signal currents between the IC and its decoupling capacitors, LC filters and power supply connection. The area directly under the IC should be treated as central ground area for the device, and all IC grounds must be connected directly to that area. A matrix of vias must be used to connect that area to the ground plane. Ground planes can be interrupted by radial traces (traces pointing away from the IC), but they must never be interrupted by circular traces, which disconnect copper outside the circular trace from copper between it and the IC. Top and bottom areas that do not contain any power or signal traces should be flooded and connected with vias to the ground plane.

Decoupling capacitors: high frequency decoupling capacitors must be located within 2 mm of the IC and connected directly to PVDD and GND pins with solid traces. Vias must not be used to complete these connections, but several vias must be used at each capacitor location to connect top ground directly to the ground plane. Placement of bulk decoupling capacitors is less critical, but they still must be placed as close as possible to the IC with strong ground return paths. Typically the heatsink sets the distance.

LC filters: LC filters must be placed as close as possible to the IC after the decoupling capacitors. The capacitors must have strong ground returns to the IC through top and bottom grounds for effective operation.

PCB copper must be at least 1 ounce thickness. PVDD and output traces must be wide enough to carry expected average currents without excessive temperature rise. PWM input traces must be kept short and close together on the input side of the IC and must be shielded with ground flood to avoid interference from high power switching signals.

The heatsink must be grounded well to the PCB near the IC, and a thin layer of highly conductive thermal compound (about 1 mil) must be used to connect the heatsink to the PowerPAD.



10.2 Layout Example



Note T1: Bottom and top layer ground plane areas are used to provide strong ground connections. The area under the IC must be treated as central ground, with IC grounds connected there and a strong via matrix connecting the area to bottom ground plane. The ground path from the IC to the power supply ground through top and bottom layers must be strong to provide very low impedance to high power and audio currents.

Note T2: Low impedance X7R or X5R ceramic high frequency decoupling capacitors must be placed within 2 mm of PVDD and GND pins and connected directly to them and to top ground plane to provide good decoupling of high frequency currents for best performance and reliability. Their dc voltage rating must be 2 x PVDD.

Note T3: Low impedance electrolytic bulk decoupling capacitors must be placed as close as possible to the IC. Typically the heat sink sets the distance. Wide PVDD traces are routed on the top layer with direct connections to the pins, without going through vias.

Note T4: LC filter inductors and capacitors must be placed as close as possible to the IC after decoupling capacitors. Inductors must have low dc resistance and switching losses and must be linear to at least the OCP (over current protection) limit. Capacitors must be linear to at least twice the maximum output voltage and must be capable of conducting currents generated by the maximum expected high frequency output.

Note T5: Bulk decoupling capacitors and LC filter capacitors must have strong ground return paths through ground plane to the central ground area under the IC.

Note T6: The heatsink must have a good thermal and electrical connection to PCB ground and to the IC PowerPAD. It must be connected to the PowerPAD through a thin layer, about 1 mil, of highly conductive thermal compound.

图 25. Printed Circuit Board - Top Layer



Layout Example (接下页)



Note B1: A wide PVDD bus and a wide ground path must be used to provide very low impedance to high power and audio currents to the power supply. Top and bottom ground planes must be connected with vias at many points to reinforce the ground connections.

Note B2: Wide output traces can be routed on the bottom layer and connected to output pins with strong via arrays.

图 26. Printed Circuit Board - Bottom Layer



11 器件和文档支持

11.1 商标

PurePath, PowerPAD are trademarks of Texas Instruments. 蓝光碟 is a trademark of Blu-ray Disk Association (BDA). All other trademarks are the property of their respective owners.

11.2 静电放电警告



这些装置包含有限的内置 ESD 保护。存储或装卸时,应将导线一起截短或将装置放置于导电泡棉中,以防止 MOS 门极遭受静电损伤。

11.3 术语表

SLYZ022 — TI 术语表。

这份术语表列出并解释术语、首字母缩略词和定义。

12 机械、封装和可订购信息

以下页中包括机械、封装和可订购信息。 这些信息是针对指定器件可提供的最新数据。 这些数据会在无通知且不 对本文档进行修订的情况下发生改变。 欲获得该数据表的浏览器版本,请查阅左侧的导航栏。

重要声明

德州仪器(TI)及其下属子公司有权根据 JESD46 最新标准,对所提供的产品和服务进行更正、修改、增强、改进或其它更改,并有权根据 JESD48 最新标准中止提供任何产品和服务。客户在下订单前应获取最新的相关信息,并验证这些信息是否完整且是最新的。所有产品的销售 都遵循在订单确认时所提供的TI 销售条款与条件。

TI保证其所销售的组件的性能符合产品销售时 TI 半导体产品销售条件与条款的适用规范。仅在 TI 保证的范围内,且 TI 认为有必要时才会使用测试或其它质量控制技术。除非适用法律做出了硬性规定,否则没有必要对每种组件的所有参数进行测试。

TI 对应用帮助或客户产品设计不承担任何义务。客户应对其使用 TI 组件的产品和应用自行负责。为尽量减小与客户产品和应 用相关的风险,客户应提供充分的设计与操作安全措施。

TI不对任何 TI 专利权、版权、屏蔽作品权或其它与使用了 TI 组件或服务的组合设备、机器或流程相关的 TI 知识产权中授予 的直接或隐含权 限作出任何保证或解释。TI 所发布的与第三方产品或服务有关的信息,不能构成从 TI 获得使用这些产品或服 务的许可、授权、或认可。使用此类信息可能需要获得第三方的专利权或其它知识产权方面的许可,或是 TI 的专利权或其它 知识产权方面的许可。

对于 TI 的产品手册或数据表中 TI 信息的重要部分,仅在没有对内容进行任何篡改且带有相关授权、条件、限制和声明的情况 下才允许进行 复制。TI 对此类篡改过的文件不承担任何责任或义务。复制第三方的信息可能需要服从额外的限制条件。

在转售 TI 组件或服务时,如果对该组件或服务参数的陈述与 TI 标明的参数相比存在差异或虚假成分,则会失去相关 TI 组件 或服务的所有明 示或暗示授权,且这是不正当的、欺诈性商业行为。TI 对任何此类虚假陈述均不承担任何责任或义务。

客户认可并同意,尽管任何应用相关信息或支持仍可能由 TI 提供,但他们将独力负责满足与其产品及在其应用中使用 TI 产品 相关的所有法 律、法规和安全相关要求。客户声明并同意,他们具备制定与实施安全措施所需的全部专业技术和知识,可预见 故障的危险后果、监测故障 及其后果、降低有可能造成人身伤害的故障的发生机率并采取适当的补救措施。客户将全额赔偿因 在此类安全关键应用中使用任何 TI 组件而 对 TI 及其代理造成的任何损失。

在某些场合中,为了推进安全相关应用有可能对 TI 组件进行特别的促销。TI 的目标是利用此类组件帮助客户设计和创立其特 有的可满足适用的功能安全性标准和要求的终端产品解决方案。尽管如此,此类组件仍然服从这些条款。

TI 组件未获得用于 FDA Class III(或类似的生命攸关医疗设备)的授权许可,除非各方授权官员已经达成了专门管控此类使 用的特别协议。

只有那些 TI 特别注明属于军用等级或"增强型塑料"的 TI 组件才是设计或专门用于军事/航空应用或环境的。购买者认可并同 意,对并非指定面向军事或航空航天用途的 TI 组件进行军事或航空航天方面的应用,其风险由客户单独承担,并且由客户独 力负责满足与此类使用相关的所有法律和法规要求。

TI 己明确指定符合 ISO/TS16949 要求的产品,这些产品主要用于汽车。在任何情况下,因使用非指定产品而无法达到 ISO/TS16949 要求,TI不承担任何责任。

	产品		应用
数字音频	www.ti.com.cn/audio	通信与电信	www.ti.com.cn/telecom
放大器和线性器件	www.ti.com.cn/amplifiers	计算机及周边	www.ti.com.cn/computer
数据转换器	www.ti.com.cn/dataconverters	消费电子	www.ti.com/consumer-apps
DLP® 产品	www.dlp.com	能源	www.ti.com/energy
DSP - 数字信号处理器	www.ti.com.cn/dsp	工业应用	www.ti.com.cn/industrial
时钟和计时器	www.ti.com.cn/clockandtimers	医疗电子	www.ti.com.cn/medical
接口	www.ti.com.cn/interface	安防应用	www.ti.com.cn/security
逻辑	www.ti.com.cn/logic	汽车电子	www.ti.com.cn/automotive
电源管理	www.ti.com.cn/power	视频和影像	www.ti.com.cn/video
微控制器 (MCU)	www.ti.com.cn/microcontrollers		
RFID 系统	www.ti.com.cn/rfidsys		
OMAP应用处理器	www.ti.com/omap		
无线连通性	www.ti.com.cn/wirelessconnectivity	德州仪器在线技术支持社区	www.deyisupport.com

邮寄地址: 上海市浦东新区世纪大道1568 号,中建大厦32 楼邮政编码: 200122 Copyright © 2015, 德州仪器半导体技术(上海)有限公司



10-Dec-2020

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
TAS5614LADDV	ACTIVE	HTSSOP	DDV	44	35	RoHS & Green	NIPDAU	Level-3-260C-168 HR	0 to 125	TAS5614LA	Samples
TAS5614LADDVR	ACTIVE	HTSSOP	DDV	44	2000	RoHS & Green	NIPDAU	Level-3-260C-168 HR	0 to 125	TAS5614LA	Samples

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

⁽²⁾ RoHS: TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".

RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.

Green: TI defines "Green" to mean the content of Chlorine (CI) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

⁽³⁾ MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

⁽⁴⁾ There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

⁽⁵⁾ Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

⁽⁶⁾ Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer:The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



www.ti.com

PACKAGE OPTION ADDENDUM

10-Dec-2020

PACKAGE MATERIALS INFORMATION

www.ti.com

Texas Instruments

TAPE AND REEL INFORMATION





QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal	
-----------------------------	--

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TAS5614LADDVR	HTSSOP	DDV	44	2000	330.0	24.4	8.6	15.6	1.8	12.0	24.0	Q1

TEXAS INSTRUMENTS

www.ti.com

PACKAGE MATERIALS INFORMATION

14-Feb-2019



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TAS5614LADDVR	HTSSOP	DDV	44	2000	350.0	350.0	43.0

GENERIC PACKAGE VIEW

PowerPAD[™] TSSOP - 1.2 mm max height

PLASTIC SMALL OUTLINE



Images above are just a representation of the package family, actual package may vary. Refer to the product data sheet for package details.



4206011/H

PACKAGE OUTLINE

DDV0044D

PowerPAD[™] TSSOP - 1.2 mm max height

PLASTIC SMALL OUTLINE



NOTES:

PowerPAD is a trademark of Texas Instruments.

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
 This drawing is subject to change without notice.
 This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not

- exceed 0.15 mm per side. 4. Reference JEDEC registration MO-153.
- 5. The exposed thermal pad is designed to be attached to an external heatsink.
- 6. Features may differ or may not be present.



DDV0044D

EXAMPLE BOARD LAYOUT

PowerPAD[™] TSSOP - 1.2 mm max height

PLASTIC SMALL OUTLINE



NOTES: (continued)

7. Publication IPC-7351 may have alternate designs.

8. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



DDV0044D

EXAMPLE STENCIL DESIGN

PowerPAD[™] TSSOP - 1.2 mm max height

PLASTIC SMALL OUTLINE



NOTES: (continued)

9. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.

10. Board assembly site may have different recommendations for stencil design.



重要声明和免责声明

Ⅱ 均以"原样"提供技术性及可靠性数据(包括数据表)、设计资源(包括参考设计)、应用或其他设计建议、网络工具、安全信息和其他资源,不保证其中不含任何瑕疵,且不做任何明示或暗示的担保,包括但不限于对适销性、适合某特定用途或不侵犯任何第三方知识产权的暗示担保。

所述资源可供专业开发人员应用TI产品进行设计使用。您将对以下行为独自承担全部责任:(1)针对您的应用选择合适的TI产品;(2)设计、 验证并测试您的应用;(3)确保您的应用满足相应标准以及任何其他安全、安保或其他要求。所述资源如有变更,恕不另行通知。TI对您使用 所述资源的授权仅限于开发资源所涉及TI产品的相关应用。除此之外不得复制或展示所述资源,也不提供其它TI或任何第三方的知识产权授权 许可。如因使用所述资源而产生任何索赔、赔偿、成本、损失及债务等,TI对此概不负责,并且您须赔偿由此对TI及其代表造成的损害。

TI所提供产品均受TI的销售条款 (http://www.ti.com.cn/zh-cn/legal/termsofsale.html) 以及ti.com.cn上或随附TI产品提供的其他可适用条款的约束。TI提供所述资源并不扩展或以其他方式更改TI 针对TI 产品所发布的可适用的担保范围或担保免责声明。

邮寄地址:上海市浦东新区世纪大道 1568 号中建大厦 32 楼,邮政编码: 200122 Copyright © 2020 德州仪器半导体技术(上海)有限公司