

BFP640F

Low profile high linearity silicon NPN RF bipolar transistor



Order now



Technical
documents



Simulation



Support

Product description

The BFP640F is a RF bipolar transistor based on SiGe:C technology that is part of Infineon's established sixth generation transistor family. Its transition frequency f_T of 42 GHz and high linearity characteristics at low currents make the device suitable for energy efficiency designs at frequency as high as 8 GHz. It remains cost competitive without compromising on ease of use.



Feature list

- Minimum noise figure $NF_{min} = 0.65$ dB at 2.4 GHz, 3 V, 6 mA
- High gain $G_{ma} = 20$ dB at 2.4 GHz, 3 V, 25 mA
- $OIP_3 = 28$ dBm at 2.4 GHz, 3 V, 25 mA

Product validation

Qualified for industrial applications according to the relevant tests of JEDEC47/20/22.

Potential applications

- Low noise amplifiers (LNAs) in GNSS receivers
- LNAs in satellite radio (SDARs, DAB) receivers
- LNAs in multimedia applications such as CATV and FM radio

Device information

Table 1 Part information

Product name / Ordering code	Package	Pin configuration				Marking	Pieces / Reel
BFP640F / BFP640FH6327XTSA1	TSFP-4-1	1 = B	2 = E	3 = C	4 = E	R4s	3000

Attention: *ESD (Electrostatic discharge) sensitive device, observe handling precautions*

Table of contents**Table of contents**

Product description	1
Feature list	1
Product validation	1
Potential applications	1
Device information	1
Table of contents	2
1 Absolute maximum ratings	3
2 Thermal characteristics	4
3 Electrical characteristics	5
3.1 DC characteristics	5
3.2 General AC characteristics	5
3.3 Frequency dependent AC characteristics	6
3.4 Characteristic DC diagrams	9
3.5 Characteristic AC diagrams	12
4 Package information TSFP-4-1	19
Revision history	20
Disclaimer	21

Absolute maximum ratings**1 Absolute maximum ratings****Table 2 Absolute maximum ratings at $T_A = 25^\circ\text{C}$ (unless otherwise specified)**

Parameter	Symbol	Values		Unit	Note or test condition
		Min.	Max.		
Collector emitter voltage	V_{CEO}	-	4.1	V	Open base
			3.6		$T_A = -55^\circ\text{C}$, open base
Collector emitter voltage			13		E-B short circuited
Collector base voltage			13		Open emitter
Emitter base voltage			1.2		Open collector
Base current	I_B	3	mA	mW	$T_S \leq 92^\circ\text{C}$
Collector current	I_C	50			
Total power dissipation ¹⁾	P_{tot}	200	$^\circ\text{C}$		$T_S \leq 92^\circ\text{C}$
Junction temperature	T_J	150			
Storage temperature	T_{Stg}	-55			

Attention: *Stresses above the max. values listed here may cause permanent damage to the device. Exposure to absolute maximum rating conditions for extended periods may affect device reliability. Exceeding only one of these values may cause irreversible damage to the integrated circuit.*

¹ T_S is the soldering point temperature. T_S is measured on the emitter lead at the soldering point of the PCB.

Thermal characteristics

2 Thermal characteristics

Table 3 Thermal resistance

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Junction - soldering point	R_{thJS}	-	-	290	K/W	-




Figure 1

Total power dissipation $P_{tot} = f(T_S)$

Electrical characteristics

3 Electrical characteristics

3.1 DC characteristics

Table 4 DC characteristics at $T_A = 25^\circ\text{C}$

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Collector emitter breakdown voltage	$V_{(\text{BR})\text{CEO}}$	4.1	4.7	-	V	$I_C = 1 \text{ mA}, I_B = 0,$ open base
Collector emitter leakage current	I_{CES}	-	1	400 ²⁾	nA	$V_{\text{CE}} = 13 \text{ V}, V_{\text{BE}} = 0,$ E-B short circuited
			1	40 ²⁾		$V_{\text{CE}} = 5 \text{ V}, V_{\text{BE}} = 0,$ E-B short circuited
			1	40 ²⁾		$V_{\text{CB}} = 5 \text{ V}, I_E = 0,$ open emitter
Collector base leakage current	I_{CBO}					
Emitter base leakage current	I_{EBO}					$V_{\text{EB}} = 0.5 \text{ V}, I_C = 0,$ open collector
DC current gain	h_{FE}	110	180	270		$V_{\text{CE}} = 3 \text{ V}, I_C = 30 \text{ mA},$ pulse measured

3.2 General AC characteristics

Table 5 General AC characteristics at $T_A = 25^\circ\text{C}$

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Transition frequency	f_T	-	42	-	GHz	$V_{\text{CE}} = 3 \text{ V}, I_C = 30 \text{ mA},$ $f = 1 \text{ GHz}$
Collector base capacitance	C_{CB}		0.09		pF	$V_{\text{CB}} = 3 \text{ V}, V_{\text{BE}} = 0,$ $f = 1 \text{ MHz},$ emitter grounded
			0.2			
			0.47			
Collector emitter capacitance	C_{CE}					$V_{\text{CE}} = 3 \text{ V}, V_{\text{BE}} = 0,$ $f = 1 \text{ MHz},$ base grounded
Emitter base capacitance	C_{EB}					$V_{\text{EB}} = 0.5 \text{ V}, V_{\text{CB}} = 0,$ $f = 1 \text{ MHz},$ collector grounded

² Maximum values not limited by the device but by the short cycle time of the 100% test.

Electrical characteristics

3.3 Frequency dependent AC characteristics

Measurement setup is a test fixture with Bias-T's in a $50\ \Omega$ system, $T_A = 25\text{ }^\circ\text{C}$.




Figure 2 Testing circuit

Table 6 AC characteristics, $V_{CE} = 3\text{ V}$, $f = 450\text{ MHz}$

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ms} $ S_{21} ^2$	-	33	-	dB	$I_C = 25\text{ mA}$
• Maximum power gain • Transducer gain			31	-		
Noise figure	NF_{min} G_{ass}	0.55	-	-	dBm	$I_C = 6\text{ mA}$
• Minimum noise figure • Associated gain			26	-		
Linearity	OIP_3 OP_{1dB}	23.5	-	-	dBm	$I_C = 25\text{ mA}, Z_S = Z_L = 50\ \Omega$
• 3rd order intercept point at output • 1 dB gain compression point at output			10.5	-		

Table 7 AC characteristics, $V_{CE} = 3\text{ V}$, $f = 900\text{ MHz}$

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ms} $ S_{21} ^2$	-	28.5	-	dB	$I_C = 25\text{ mA}$
• Maximum power gain • Transducer gain			26.5	-		
Noise figure	NF_{min} G_{ass}	0.55	-	-	dBm	$I_C = 6\text{ mA}$
• Minimum noise figure • Associated gain			23.5	-		
Linearity	OIP_3 OP_{1dB}	26	-	-	dBm	$I_C = 25\text{ mA}, Z_S = Z_L = 50\ \Omega$
• 3rd order intercept point at output • 1 dB gain compression point at output			12.5	-		

Electrical characteristics

Table 8 AC characteristics, $V_{CE} = 3$ V, $f = 1.5$ GHz

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ms} $ S_{21} ^2$	-	25 22.5	-	dB	$I_C = 25$ mA
• Maximum power gain						
• Transducer gain						
Noise figure	NF_{min} G_{ass}		0.6 20.5		dBm	$I_C = 6$ mA
• Minimum noise figure						
• Associated gain						
Linearity	OIP_3 OP_{1dB}		26 12		dBm	$I_C = 25$ mA, $Z_S = Z_L = 50$ Ω
• 3rd order intercept point at output						
• 1 dB gain compression point at output						

Table 9 AC characteristics, $V_{CE} = 3$ V, $f = 1.9$ GHz

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ms} $ S_{21} ^2$	-	23 20.5	-	dB	$I_C = 25$ mA
• Maximum power gain						
• Transducer gain						
Noise figure	NF_{min} G_{ass}		0.6 19		dBm	$I_C = 6$ mA
• Minimum noise figure						
• Associated gain						
Linearity	OIP_3 OP_{1dB}		27 12.5		dBm	$I_C = 25$ mA, $Z_S = Z_L = 50$ Ω
• 3rd order intercept point at output						
• 1 dB gain compression point at output						

Table 10 AC characteristics, $V_{CE} = 3$ V, $f = 2.4$ GHz

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ma} $ S_{21} ^2$	-	20 18.5	-	dB	$I_C = 25$ mA
• Maximum power gain						
• Transducer gain						
Noise figure	NF_{min} G_{ass}		0.65 17		dBm	$I_C = 6$ mA
• Minimum noise figure						
• Associated gain						
Linearity	OIP_3 OP_{1dB}		28 12.5		dBm	$I_C = 25$ mA, $Z_S = Z_L = 50$ Ω
• 3rd order intercept point at output						
• 1 dB gain compression point at output						

Electrical characteristics

Table 11 AC characteristics, $V_{CE} = 3$ V, $f = 3.5$ GHz

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ma} $ S_{21} ^2$	–	16.5	–	dB	$I_C = 25$ mA
• Maximum power gain • Transducer gain			15.5	–		
Noise figure	NF_{min} G_{ass}	–	0.75	–	dBm	$I_C = 6$ mA
• Minimum noise figure • Associated gain			14	–		
Linearity	OIP_3 OP_{1dB}	–	27.5	–	dBm	$I_C = 25$ mA, $Z_S = Z_L = 50 \Omega$
• 3rd order intercept point at output • 1 dB gain compression point at output			12	–		

Table 12 AC characteristics, $V_{CE} = 3$ V, $f = 5.5$ GHz

Parameter	Symbol	Values			Unit	Note or test condition
		Min.	Typ.	Max.		
Power gain	G_{ma} $ S_{21} ^2$	–	12.5	–	dB	$I_C = 25$ mA
• Maximum power gain • Transducer gain			11.5	–		
Noise figure	NF_{min} G_{ass}	–	1.0	–	dBm	$I_C = 6$ mA
• Minimum noise figure • Associated gain			11	–		
Linearity	OIP_3 OP_{1dB}	–	27.5	–	dBm	$I_C = 25$ mA, $Z_S = Z_L = 50 \Omega$
• 3rd order intercept point at output • 1 dB gain compression point at output			12.5	–		

Note: $G_{ms} = |S_{21}| / S_{12}|$ for $k < 1$; $G_{ma} = |S_{21}| / S_{12}| / (k - (k^2 - 1)^{1/2})$ for $k > 1$. In order to get the NF_{min} values stated in this chapter, the test fixture losses have been subtracted from all measured results. OIP_3 value depends on termination of all intermodulation frequency components. Termination used for this measurement is 50Ω from 0.2 MHz to 12 GHz.

Electrical characteristics

3.4

Characteristic DC diagrams



Figure 3 Collector current vs. collector emitter voltage $I_C = f(V_{CE})$, I_B = parameter

Figure 4

DC current gain $h_{FE} = f(I_C)$, $V_{CE} = 3$ V

Electrical characteristics




Figure 5 Collector current vs. base emitter forward voltage $I_C = f(V_{BE})$, $V_{CE} = 2$ V







Figure 6 Base current vs. base emitter forward voltage $I_B = f(V_{BE})$, $V_{CE} = 2$ V

Electrical characteristics**Figure 7****Base current vs. base emitter reverse voltage $I_B = f(V_{EB})$, $V_{CE} = 2$ V**

Electrical characteristics

3.5

Characteristic AC diagrams

Figure 8 Transition frequency $f_T = f(I_C)$, $f = 1$ GHz, V_{CE} = parameterFigure 9 3rd order intercept point $OIP_3 = f(I_C)$, $Z_S = Z_L = 50 \Omega$, V_{CE} , f = parameters

Electrical characteristics




Figure 10

3rd order intercept point at output OIP_3 [dBm] = $f(I_C, V_{CE})$, $Z_S = Z_L = 50 \Omega$, $f = 2.4$ GHz








Figure 11

Compression point at output OP_{1dB} [dBm] = $f(I_C, V_{CE})$, $Z_S = Z_L = 50 \Omega$, $f = 2.4$ GHz

Electrical characteristics

Figure 12 Collector base capacitance $C_{CB} = f(V_{CB})$, $f = 1$ MHzFigure 13 Gain G_{ma} , G_{ms} , $|S_{21}|^2 = f(f)$, $V_{CE} = 3$ V, $I_C = 25$ mA

Electrical characteristics

Figure 14 Maximum power gain $G_{max} = f(I_C)$, $V_{CE} = 3$ V, f = parameter in GHzFigure 15 Maximum power gain $G_{max} = f(V_{CE})$, $I_C = 25$ mA, f = parameter in GHz

Electrical characteristics




Figure 16 Input reflection coefficient $S_{11} = f(f)$, $V_{CE} = 3 \text{ V}$, $I_C = 6 / 25 \text{ mA}$








Figure 17 Source impedance for minimum noise figure $Z_{S,\text{opt}} = f(f)$, $V_{CE} = 3 \text{ V}$, $I_C = 6 / 25 \text{ mA}$

Electrical characteristics

Figure 18 Output reflection coefficient $S_{22} = f(f)$, $V_{CE} = 3$ V, $I_C = 6 / 25$ mAFigure 19 Noise figure $NF_{min} = f(f)$, $Z_S = Z_{S,opt}$, $V_{CE} = 3$ V, $I_C = 6 / 25$ mA

Electrical characteristics

Figure 20 Noise figure $NF_{min} = f(I_C)$, $Z_S = Z_{S,opt}$, $V_{CE} = 3\text{ V}$, $f = \text{parameter in GHz}$ Figure 21 Noise figure $NF_{50} = f(I_C)$, $Z_S = 50\Omega$, $V_{CE} = 3\text{ V}$, $f = \text{parameter in GHz}$

Note:

The curves shown in this chapter have been generated using typical devices but shall not be considered as a guarantee that all devices have identical characteristic curves. $T_A = 25^\circ\text{C}$.

Package information TSFP-4-1

4 Package information TSFP-4-1




Figure 22 Package outline




Figure 23 Foot print




Figure 24 Marking layout example




Figure 25 Tape dimensions

Revision history**Revision history**

Document version	Date of release	Description of changes
Revision 3.0	2019-01-25	New datasheet layout.

Trademarks

All referenced product or service names and trademarks are the property of their respective owners.

Edition 2019-01-25

Published by

**Infineon Technologies AG
81726 Munich, Germany**

**© 2019 Infineon Technologies AG
All Rights Reserved.**

Do you have a question about any aspect of this document?

Email: erratum@infineon.com

**Document reference
IFX-umi1526292225260**

IMPORTANT NOTICE

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics ("Beschaffenheitsgarantie").

With respect to any examples, hints or any typical values stated herein and/or any information regarding the application of the product, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party.

In addition, any information given in this document is subject to customer's compliance with its obligations stated in this document and any applicable legal requirements, norms and standards concerning customer's products and any use of the product of Infineon Technologies in customer's applications.

The data contained in this document is exclusively intended for technically trained staff. It is the responsibility of customer's technical departments to evaluate the suitability of the product for the intended application and the completeness of the product information given in this document with respect to such application.

WARNINGS

Due to technical requirements products may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies office.

Except as otherwise explicitly approved by Infineon Technologies in a written document signed by authorized representatives of Infineon Technologies, Infineon Technologies' products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury